



JVC

SERVICE MANUAL

AUDIO/VIDEO CONTROL RECEIVER

RX-E100RSL RX-E100RSB



Area Suffix

RX-E100RSL

B U.K.
E Continental Europe
EN Northern Europe

RX-E100RSB

E Continental Europe
EN Northern Europe



Each difference points

MODEL	Source indication lens colour
RX-E100RSL	SILVER
RX-E100RSB	SILVER BLACK

Contents

Safety precautions	1- 2
Disassembly method	1- 3
Adjustment method	1- 8
Description of major ICs	1- 9 ~ 15

Safety Precautions

1. This design of this product contains special hardware and many circuits and components specially for safety purposes. For continued protection, no changes should be made to the original design unless authorized in writing by the manufacturer. Replacement parts must be identical to those used in the original circuits. Services should be performed by qualified personnel only.
2. Alterations of the design or circuitry of the product should not be made. Any design alterations of the product should not be made. Any design alterations or additions will void the manufacturer's warranty and will further relieve the manufacture of responsibility for personal injury or property damage resulting therefrom.
3. Many electrical and mechanical parts in the products have special safety-related characteristics. These characteristics are often not evident from visual inspection nor can the protection afforded by them necessarily be obtained by using replacement components rated for higher voltage, wattage, etc. Replacement parts which have these special safety characteristics are identified in the Parts List of Service Manual. Electrical components having such features are identified by shading on the schematics and by ($\triangle$) on the Parts List in the Service Manual. The use of a substitute replacement which does not have the same safety characteristics as the recommended replacement parts shown in the Parts List of Service Manual may create shock, fire, or other hazards.
4. The leads in the products are routed and dressed with ties, clamps, tubings, barriers and the like to be separated from live parts, high temperature parts, moving parts and/or sharp edges for the prevention of electric shock and fire hazard. When service is required, the original lead routing and dress should be observed, and it should be confirmed that they have been returned to normal, after re-assembling.
5. Leakage current check (Electrical shock hazard testing)

After re-assembling the product, always perform an isolation check on the exposed metal parts of the product (antenna terminals, knobs, metal cabinet, screw heads, headphone jack, control shafts, etc.) to be sure the product is safe to operate without danger of electrical shock.


Do not use a line isolation transformer during this check.

- Plug the AC line cord directly into the AC outlet. Using a "Leakage Current Tester", measure the leakage current from each exposed metal parts of the cabinet, particularly any exposed metal part having a return path to the chassis, to a known good earth ground. Any leakage current must not exceed 0.5mA AC (r.m.s.).

- Alternate check method

Plug the AC line cord directly into the AC outlet. Use an AC voltmeter having, 1,000 ohms per volt or more sensitivity in the following manner. Connect a 1,500 Ω 10W resistor paralleled by a 0.15 μ F AC-type capacitor between an exposed metal part and a known good earth ground. Measure the AC voltage across the resistor with the AC voltmeter.

Move the resistor connection to each exposed metal part, particularly any exposed metal part having a return path to the chassis, and measure the AC voltage across the resistor. Now, reverse the plug in the AC outlet and repeat each measurement. Any voltage measured must not exceed 0.75 V AC (r.m.s.). This corresponds to 0.5 mA AC (r.m.s.).



Warning

1. This equipment has been designed and manufactured to meet international safety standards.
2. It is the legal responsibility of the repairer to ensure that these safety standards are maintained.
3. Repairs must be made in accordance with the relevant safety standards.
4. It is essential that safety critical components are replaced by approved parts.
5. If mains voltage selector is provided, check setting for local voltage.

CAUTION

Burrs formed during molding may be left over on some parts of the chassis. Therefore, pay attention to such burrs in the case of preforming repair of this system.


In regard with component parts appearing on the silk-screen printed side (parts side) of the PWB diagrams, the parts that are printed over with black such as the resistor ($\blacksquare$), diode ($\blacksquare$) and ICP ($\bullet$) or identified by the " $\triangle$ " mark nearby are critical for safety.

When replacing them, be sure to use the parts of the same type and rating as specified by the manufacturer. (Except the JC version)

Disassembly method

■ Removing the top cover (See Fig.1)



1. Remove the four screws A attaching the top cover on both sides of the body.
2. Remove the three screws B on the back of the body.
3. Remove the top cover from behind in the direction of the arrow while pulling both sides outward.



■ Removing the front panel assembly (See Fig.2 and 3)

- Prior to performing the following procedure, remove the top cover.

1. Disconnect the card wire from connector CN411 on the audio board, CN412 on the input board and CN204 on the power supply board in the front panel assembly.
2. Cut off the tie band fixing the harness.
3. Remove the three screws C attaching the front panel assembly.
4. Remove the four screws D attaching the front panel assembly on the bottom of the body. Detach the front panel assembly toward the front.



■ Removing the rear panel (See Fig.4)

- Prior to performing the following procedure, remove the top cover.

1. Remove the power cord stopper from the rear panel by moving it in the direction of the arrow.
2. Remove the twenty one screws E attaching the each boards to the rear panel on the back of the body.
3. Remove the four screws F attaching the rear panel on the back of the body.




Fig.4

■ Removing each board connected to the rear side of the audio board

(See Fig.5 to 7)

- Prior to performing the following procedure, remove the top cover and the rear panel.

1. Cut off the tie band fixing the harness.
2. Disconnect the tuner board and DSP board from connector CN111, CN112 and CN681 on the each Relay board.
3. Disconnect the Relay board from connector CN503, CN504 and CN501 on the audio board.
4. Disconnect the card wire connected to connector CN412 and CN512 on the Input board.




Fig.5




Fig.6




Fig.7

■ Removing the audio board (See Fig.8)

- Prior to performing the following procedure, remove the top cover, the rear panel and the each board.
1. Disconnect the card wire from connector CN411 on the audio board.
 2. Disconnect the harness from connector CN205 on the audio board.
 3. Disconnect the harness from connector CN515, CN516, and CN517 on the main board.
 4. Remove the harness band fixing the harness.
 5. Remove the three screws G attaching the audio board assembly.




Fig.8

■ Removing the main board (See Fig.9)

- Prior to performing the following procedure, remove the top cover, the rear panel and audio board.
1. Remove the harness band fixing the harness.
 2. Disconnect the harness from connector CN707 on the power supply board.
 3. Disconnect the harness from connector CN202 and CN206 on the main board.
 4. Remove the five screws H and the two screws I attaching the main board.




Fig.9

■ Removing the Heat sink (See Fig.10 to 11)

1. Remove the ten screws K and four screws L attaching the heat sink.
2. Remove the two screws J attaching the heat sink from the rear side of main board.




Fig.10




Fig.11

■ Removing the power supply board (See Fig.12)

- Prior to performing the following procedure, remove the top cover.
1. Disconnect the card wire from connector CN204 on the power supply board.
 2. Disconnect the harness connected to connector CN707 on the power supply board (If necessary, cut off the band fixing the harness on the side of the base chassis).
 3. Disconnect the harness connected to connector CN206 on the main board
 4. Remove the three screws N attaching the power supply board.
 5. Unsolder the three harnesses connected to the power supply board.




Fig.12

■ Removing the power transformer (See Fig.12 and 13)

- Prior to performing the following procedures, remove the top cover.
1. Disconnect the harness from connector CN217 on the power / fuse board.
 2. Disconnect the harness from connector CN201 and CN202 on the power supply board and main board.
 3. Remove the four screws M attaching the power transformer.




Fig.13

■ Removing the power / fuse board (See Fig.13)

- Prior to performing the following procedure, remove the top cover and the rear panel.
1. Disconnect the harness connected to connector CN217 on the power / fuse board (If necessary, cut off the band fixing the harness on the side of the base chassis).
 2. Unsolder the power cord and other harnesses connected to the power / fuse board.
 3. Remove the screw O attaching the power / fuse board.

■ Removing the system control board / power switch board (See Fig.14)

- Prior to performing the following procedure, remove the top cover and the front panel assembly.
1. Remove the two screws P attaching the power switch board.
 2. Remove the eight screws Q attaching the system control board.




Fig.14

Adjustment method

■ Power amplifier section

Adjustment of idling current

Measurement terminal B451-B452(Lch) , B453-B454(Rch)

Adjustment volume VR301(Lch) , VR302(Rch)

Attention


This adjustment does not obtain a correct adjustment value immediately after the amplifier is used (state that an internal temperature has risen).

Please adjust immediately after using the amplifier after turning off the power supply of the amplifier and falling an internal temperature.

<Adjustment method>

1. Prior to turning the power ON, fully turn the adjusting resistor (VR301(Lch),VR302(Rch)) counterclockwise direction and connect the DC voltmeter to the measuring terminal(B451-B452(Lch) , B453-B454(Rch)).
2. Set the surround mode OFF.
3. Adjust the resistor so that the measured value becomes 2mV immediately after turning the power ON.
4. When the idling current has been stable (about 30 minutes after the power is turned ON), confirm that the measured value falls within 1.0mV~10mV(2.3mV).


* It is not abnormal though the idling current might not become 0mA even if it is finished to turn variable resistance (VR301VR302) in the direction of counterclockwise.



Description of major ICs

■ AK4527B (IC601) : A/D,D/A Converter

1.Pin layout



2. Pin function (1/2)

AK4527(1/2)

No.	Pin name	I/O	Function
1	SDOS	I	SDTO Source Select Pin (Note 1) "L" : Internal ADC output, "H" : DAUX input
2	I2C	I	Control Mode Select Pin "L" : 3-wire Serial, "H" : I2C Bus
3	SMUTE	I	Soft Mute Pin (Note 1) When this pin goes to "H", soft mute cycle is initialized. When returning to "L", the output mute releases.
4	BICK	I	Audio Serial Data Clock Pin
5	LRCK	I/O	Input Channel Clock Pin
6	SDTI1	I	DAC1 Audio Serial Data Input Pin
7	SDTI2	I	DAC2 Audio Serial Data Input Pin
8	SDTI3	I	DAC3 Audio Serial Data Input Pin
9	SDTO	O	Audio Serial Data Output Pin
10	DAUX	I	Sub Audio Serial Data Input Pin
11	DFS	I	Double Speed Sampling Mode Pin (Note 1) "L" : Normal Speed, "H" : Double Speed
12	NC	-	No Connect No internal bonding.
13	DZFE	I	Zero Input Detect Enable Pin "L" : mode 7 (disable) at parallel mode, zero detect mode is selectable by DZFM2-0 bits at serial mode. "H" : mode 0 (DZF is AND of all six channels)
14	TVDD	-	Output Buffer Power supply Pin, 2.7V~5.5V
15	DVDD	-	Digital Power Supply Pin, 4.5V~5.5V
16	DVSS	-	De-emphasis Pin, 0V
17	PDN	I	Power-Down & Reset Pin When "L", the AK4527B is powered-down and the control registers are reset to default state. If the state of P/S or CAD0-1 changes, then the AK4527B must be reset by PDN.
18	TST	I	Test Pin This pin should be connected to DVSS.

Pin function (2/2)


AK4527(1/2)

No.	Pin name	I/O	No Connect	Function
19	NC	-	No internal bonding.	Analog Input Format Select Pin
20	ADIF	I	"H" : Full-differential input, "L" : Single-ended input	Chip Address 1 Pin
21	CAD1	I		Chip Address 0 Pin
22	CAD0	I		DAC3 Lch Analog Output Pin
23	LOUT3	O		DAC3 Rch Analog Output Pin
24	ROUT3	O		DAC2 Lch Analog Output Pin
25	LOUT2	O		DAC2 Rch Analog Output Pin
26	ROUT2	O		DAC1 Lch Analog Output Pin
27	LOUT1	O		DAC1 Rch Analog Output Pin
28	ROUT1	O		Lch Analog Negative Input Pin
29	LIN-	I		Lch Analog Positive Input Pin
30	LIN+	I		Rch Analog Negative Input Pin
31	RIN-	I		Rch Analog Positive Input Pin
32	RIN+	I		Zero Input Detect 2 Pin (Note 2)
33	DZF2	O	When the input data of the group 1 follow total 8192LRCK cycles with "0" input data, this pin goes to "H". Analog Input Overflow Detect Pin (Note 3)	
	OVF	O	This pin goes to "H" if the analog input of Lch or Rch is overflows. Common Voltage Output Pin,AVDD/2	
34	VCOM	O	Large external capacitor around 2.2uF is used to reduce power-supply noise. Positive Voltage Reference Input Pin,AVDD	
35	VREFH	I	Analog Power Supply Pin,4.5V~5.5V	
36	AVDD	-	Analog Ground Pin,0V	
37	AVSS	-	Zero Input Detect 1 Pin (Note 2)	
38	DZF1	O	When the input data of the group 1 follow total 8192 LRCK cycles with "0" input data, this pin goes to "H". Master Clock Input Pin	
39	MCLK	I	Parallel / Serial Select Pin	
40	P/S	I	"L" : Serial control mode, "H" : Parallel control mode Audio Data Interface Format 0 Pin in parallel mode	
41	DIF0	I	Chip select pin in 3-wire serial control mode	
	CSN	I	This pin should be connected to DVDD at I2C bus control mode Audio Data Interface Format 1 Pin in parallel mode	
42	DIF1	I	Control Data Clock Pin in serial control mode	
	SCL/CCLK	I	I2C = "L" : CCLK(3-wire Serial), I2C = "H" : SCL(I2CBus) Loopback Mode 0 Pin in parallel control mode	
43	LOOP0	I	Enables digital loop-back from ADC to 3 DACs. Control Data Input Pin in serial control mode	
	SAD/CDTI	I/O	I2C = "L" : CDTI(3-wire Serial), I2C = "H" : SDA(I2CBus) Loopback Mode 1 Pin (Note 1)	
44	LOOP1	I	Enable all 3 DAC channels to be input from SDTII.	

- Notes : 1. SDOS, SMUTE, DFS, and LOOP1 pins are ORed with register data if P/S = "L".
 2. The group 1 and 2 can be selected by DZFM2-0 bit if P/S = "L" and DZFME = "L".
 3. This pin becomes OVF pin if OVFE bit is set to "1" at serial control mode.
 4. All input pins should not be left floating.

■ UPD784215AGC103 (IC671) : UNIT CPU

1.Pin layout



2.Pin function

Pin No.	Symbol	I/O	Function
1~8		-	Non connect
9	VDD	-	Power supply terminal
10	X2	O	Connecting the crystal oscillator for system main clock
11	X1	I	Connecting the crystal oscillator for system main clock
12	VSS	-	Connect to GND
13	XT2	O	Connecting the crystal oscillator for system sub clock
14	XT1	I	Connecting the crystal oscillator for system sub clock
15	RESET	I	System reset signal input
16	AUTODATA	I	Output of DSP to general-purpose port
17	LOCK	I	Output of DSP to general-purpose port
18	DIGITAL0	I	Output of DSP to general-purpose port
19	FORMAT	I	Output of DSP to general-purpose port
20	CHANNEL	I	Output of DSP to general-purpose port
21	ERR	I	Output of DSP to general-purpose port
22	RSTDET	I	Reset signal input
23	AVDD	-	Power supply terminal
24	AVREF0	-	Connect to GND
25~32		-	Connect to GND
33	AVSS	-	Connect to GND
34,35		-	Non connect
36	AV REF1	-	Power supply terminal
37,38	RX,TX	-	Not use
39		-	Non connect
40	DSPCOM	I	Communication port from IC701
41	DSPSTS	O	Status communication port to IC701
42	DSPCLK	I	Clock input from IC701
43	DSPRDY	I	Ready signal input from IC701
44		-	Non connect
45,46	MIDIO IN/OUT	I/O	Interface I/O terminal with microcomputer
47	MICK	O	Interface I/O terminal with microcomputer of clock signal
48	MICS	O	Interface I/O terminal with microcomputer of chip select
49	MILP	O	Interface I/O terminal with microcomputer
50	MIACK	O	Interface I/O terminal with microcomputer
51,52		-	Non connect
53	DSPRST	O	Reset signal output of DSP
54~63		-	Non connect
64,65	CDTI/CDTO	I/O	Interface I/O terminal with microcomputer
66	CCLK	O	Interface I/O terminal with microcomputer of clock signal
67	CS	O	Interface I/O terminal with microcomputer of chip select
68	XTS	O	OSC Select
69,70		-	Non connect
71	PD	O	Reset signal output
72	GND	-	Connect to GND
73~80		-	Non connect
81	VDD	-	Power supply
82	3D-ON	-	Non connect
83	3D-ON	O	Switch at output destination of surround channel
84	ANA/T-TONE	O	Test tone control
85	REF-MIX	O	Control at output destination of LFE channel
86		-	Non connect
87	D.MUTE	O	Mute of the digital out terminal is controlled
88	S.MUTE	O	Mute of the audio signal is controlled
89		-	Non connect
90~93	ASW1~4	O	Selection of digital input selector
94	TEST	-	Test terminal
95~100		-	Non connect


**■ TC9446F-014 (IC631) : Digital signal processor for dolby digital (AC-3)
/ MPEG2 audio decode**

Pin No.	Symbol	I/O	Function
1	$\overline{\text{RST}}$	I	Reset signal input terminal (L:reset H:Operation usually)
2	MIMD	I	Microcomputer interface mode selection input terminal (L:serial H:IC bus)
3	MICS	I	Microcomputer interface chip select input terminal
4	MILP	I	Microcomputer interface latch pulse input
5	MIDIO	I/O	Microcomputer interface data I/O terminal
6	MICK	I	Microcomputer interface clock input terminal
7	MIACK	O	Microcomputer interface acknowledge output terminal
8~11	FI0~3	I	Flag input terminal 0~3
12	IRQ	I	Interrupt input terminal
13	VSS	-	Digital ground terminal
14	LRCKA	I	Audio interface LR clock input terminal A
15	BCKA	I	Audio interface bit clock input terminal A
16~18	SDO0~2	O	Audio interface data output terminal 0
19	SD03	-	Non connect
20	LRCKB	I	Audio interface LR clock input terminal B
21	BCKB	I	Audio interface bit clock input terminal B
22	SDT0	I	Audio interface data input terminal 0
23	SDT1	I	Audio interface data input terminal 1
24	VDD	-	Power supply for digital circuit
25	LRCKOA	O	Audio interface LR clock output terminal A
26	BCKOA	O	Audio interface bit clock output terminal A
27,28	TEST0,1	I	Test input terminal 0/1 (L:test H:operation usually)
29~31	LRCKOB,BCKOB,TXO	-	Non connect
32,33	TEST2,3	I	Test input terminal (L:test H:operation usually)
34	RX	I	SPDIF input terminal
35	VSS	-	Ground terminal for digital circuit
36	TSTSUB0	I	Test sub input terminal 0 (L:test H:operation usually)
37	FCONT	O	VCO Frequency control output terminal
38,39	TSTSUB1,TSTSUB2	I	Test sub input terminal 1,2 (L:test H:operation usually)
40	PDO	O	Phase error signal output terminal
41	VDDA	-	Power supply for analog circuit
42	PLON	I	Clock selection input terminal (L:external clock H:VCO clock)
43	AMPI	I	AMP.input terminal for LPF
44	AMPO	O	AMP.output terminal for LPF
45	CKI	I	External clock input terminal
46	VSSA	-	Ground terminal for analog circuit
47	CKO	O	DIR Clock output terminal
48	LOCK	O	VCO Lock detection output terminal
49	VSS	-	Ground terminal for digital circuit
50	WR	O	External SRAM writing signal output terminal
51	$\overline{\text{OE}}$	O	External SRAM output enable signal output terminal
52	$\overline{\text{CE}}$	O	External SRAM chip enable signal output terminal
53	VDD	-	Power supply terminal for digital circuit
54~61	IO7~0	I/O	External SRAM data I/O terminal 7~0
62	VSS	-	Ground terminal for digital circuit
63~70	AD0~7	O	External SRAM address output terminal 0~7
71	VDD	-	Power supply terminal for digital circuit
72~80	AD8~16	O	External SRAM address output terminal 8~16
81	VSS	-	Ground terminal for digital circuit
82~89	PO0~7	O	General purpose output terminal 0~7
90	VDDDL	-	Power supply terminal for DLL
91	LPFO	O	LPF output terminal for DLL
92,93	DLON,DLCKS	I	Refer to the undermentioned table
94	SCKO	-	Non connect
95	VSSDL	-	Ground terminal for DLL
96	SCKI	I	External system clock input terminal
97	VSSX	-	Ground terminal for oscillation circuit
98,99	XO,XI	I/O	Oscillation I/O terminal
100	VDDX	-	Power supply terminal for oscillation circuit


DLCKS terminal	DLONterminal	DLL clock setting
L	L	SCKI input (DLL circuit OFF)
L	H	Four times XI clock
H	L	Three times XI clock
H	H	Six times XI clock

■ W24L010AJ-12 (IC641) : CMOS SRAM


Block diagram




Pin layout




■ PQ3DZ53 (IC681) : Regulator IC



■ RN5RZ33BA (IC683) : Voltage regulator



■ MN101C35DHR (IC401) : System controller



Pin function (1/2)


Pin No.	Symbol	I/O	Function
1	TXD/SB00/P00	-	GND
2	RXD/SBI0/P01	-	GND
3	SBT0/P02	I	PROTECTOR INPUT
4	SB01/P03	-	GND
5	SBI1/P04	-	GND
6	SBT1/P05	I	GND (TV LINK INPUT)
7	BUZZER/P06	I	SLOW SW L INPUT
8	VDD	-	POWER SUPPLY +5V
9,10	OSC1,2	I/O	OSC (8MHz)
11	VSS	-	GND
12	XI	-	GND
13	X0	O	OPEN
14	MMOD	-	GND
15	VREF-	-	GND
16	AN0/PA0	I	KEY INPUT 1 (7KEY)
17	AN1/PA1	I	KEY INPUT 2 (7KEY)
18	AN2/PA2	I	KEY INPUT 3 (7KEY)
19	AN3/PA3	I	CHIP SELECT 1
20	AN4/PA4	I	CHIP SELECT 2
21	AN5/PA5	I	SCART DVD INPUT
22	AN6/PA6	I	SCART STB INPUT
23	AN7/PA7	I	SCART VCR INPUT
24	VREF+	-	POWER SUPPLY +5V
25	P07	O	SLOW SW M OUTPUT
26	RST /P27	I	RESET INPUT
27	TM0IO/P10	O	RDS SDA IN/OUT
28	TM1IO/P11	I	RDS SCL IN/OUT
29	TM2IO/P12	O	TUNER CE
30	TM3IO/P13	I	TUNER MUTE
31	TM4IO/P14	O	TUNER CLK
32	P15	I/O	TUNER DATA IN/OUT
33	IRQ0/P20	-	GND
34	SENS/IRQ1/P21	I	REMOCON INPUT
35	IRQ2/P22	I	INH INPUT
36	IRQ3/P23	I	RDS DAVN INPUT
37	IRQ4/P24	I	TUNED INPUT
38	P25	I	STEREO INPUT
39	SB02/P30	O	DSP MICON COMMAND
40	SBI2/P31	I	DSP MICON STATUS

Pin function (2/2)

Pin No.	Symbol	I/O	Function
41	SBT2/P32	O	DSP MICON CLK
42	P50	O	DSP MICON READY
43	P51	O	DSP MICON RESET
44	P52	O	M61501 CLK
45	P53	O	M61501 DATA
46	P54	O	M61501 LATCH
47 50	DGT17/P67 DGT14/P64	O	VIDEO SELECT 1 VIDEO SELECT 4
51 54	DGT13/P63 DGT10/P60	O	GRID 1 GRID 4
55	DGT9/P41	O	GRID 5
56	DGT8/P40	O	GRID 6
57 63	SEG0/DGT7/P77 SEG6/DGT1/P71	O	GRID 7 GRID 13
64	SEG7/DGY0/P7	O	SEGMENT 17
65 72	SEG8/P87 SEG15/P80	O	SEGMENT 18 SEGMENT 25
73 88	SEG16/P97 SEG31/PB3	O	SEGMENT 1 SEGMENT 16
89	SEG32/PB2	O	STANDBY LED
90	SEG33/PB1	O	EXPANSION BU2092 LCK
91	SEG34/PB0	O	EXPANSION BU2092 DATA
92	SEG35/PD7	O	EXPANSION BU2092 CLK
93	SEG36/PD6	O	FRONT SPK RELAY
94	SEG37/PD5	O	CENTER SPK RELAY
95	SEG38/PD4	O	REAR SPK RELAY
96	SEG39/PD3	O	POWER ON
97	SEG40/PD2	O	SWITCH MODE ON
98	SEG41/PD1	O	SUBWFR MUTE
99	SEG42/PD0	O	SOURCE MUTE
100	VPP	O	VPP

■ BU2092 (IC642) : Port expander

1.Terminal Layout




2.Pin Function

Pin No.	Symbol	I/O	Function						
1	Vss	-	Connect to GND						
2	DATA	I	Serial Data input						
3	CLOCK	I	Shift Clock of Data						
4	LCK	I	Latch Clock of Data						
5~16	Q0~Q11	O	Parallel Data Output						
			<table><tr><td>Latch Data</td><td>L</td><td>H</td></tr><tr><td>OUTPUT</td><td>ON</td><td>OFF</td></tr></table>	Latch Data	L	H	OUTPUT	ON	OFF
			Latch Data	L	H				
OUTPUT	ON	OFF							
17	$\overline{\text{OE}}$	I	Output Enable						
18	Vdd	-	Power Supply						

■ NJM2246M (IC511,IC512,IC513) : Video switch

Block diagram




INPUT CONTROL SIGNAL- OUTPUT SIGNAL


CTL1	CTL2	OUTPUT SIGNAL
L	L	Vin1
H	L	Vin2
L/ H	H	Vin3

■ NJM2267M (IC516) : Video switch

1. Pin layout




2. Block diagram




■ NJM2279M (IC515) : Video switch

1. Pin layout




2. Block diagram



■ NJM2293 (IC514) : Video switch

Block diagram



RX-E100RSL/RX-E100RSB

JVC

VICTOR COMPANY OF JAPAN, LIMITED

AUDIO & COMMUNICATION BUSINESS DIVISION

PERSONAL & MOBILE NETWORK BUSINESS UNIT. 10-1,1chome,Ohwatari-machi,Maebashi-city,371-8543,Japan

(No.20951)



Printed in Japan
200105(V)

PARTS LIST

[RX-E100RSL]
[RX-E100RSB]

* All printed circuit boards and its assemblies are not available as service parts.

RX-E100RSL
Area suffix
B ----- U.K.
E ----- Continental Europe
EN ----- Northern Europe

RX-E100RSB
Area suffix
E ----- Continental Europe
EN ----- Northern Europe


- Contents -

Exploded view of general assembly and parts list	3- 3
Electrical parts list	3- 5
Packing materials and accessories parts list	3-18

< M E M O >

Exploded view of general assembly and parts list

Block No. M 1 M M



■ Parts list (General assembly)

Block No. M1MM

⚠	Item	Parts number	Parts name	Q'ty	Description	Area
⚠	1	LV10482-001A	FRONT PANEL	1		
	2	VJD5429-002SS	JVC MARK	1		
	3	E75896-003	FELT SPACER	2	FOR FRONT FOOT	
	4	LV20958-005A	LENS	1	RX-E100RSB	
		LV20958-001A	LENS	1	RX-E100RSL	
	5	LV20991-001A	POWER BUTTON	1		
	6	LV42096-001A	INDICATOR	1		
	7	LV32517-001A	CONTROL BUTTON	1		
	8	LV20959-001A	SOURCE BUTTON	1		
	9	LV32519-001A	SOURCE INDICATO	2		
	10	LV32552-003A	INDI.ESCUTCHEON	1		
	11	LV20992-001A	VOLUME BUTTON	1		
	12	QYSBSF2608Z	T.SCREW	2	F.C.B POWER+F.PANEL	
	13	LV42195-001A	FL SCREEN	1	TO FRONT PANEL	
	14	QYSBSF2608Z	T.SCREW	8	F.C.B FL+F.PANEL	
	15	QUQ412-1448CJ	FFC WIRE	1		
	16	QUQ412-1738CJ	FFC WIRE	1		
	17	QUQ412-1213CJ	FFC WIRE	1		
	18	QYSBSG3006Z	T.SCREW	4	F.PANEL+C.BASE	
	19	QYSBSG3006Z	T.SCREW	3	F.PANEL+F.BKT	
	20	LV10019-003A	CHASSIS BASE	1		
	21	LV10483-001A	FRONT BRACKET	1		
	22	QYSBSG3006Z	T.SCREW	5	C.BASE+F.BKT	
	23	E68587-223SM	CB BKT	3		
	24	QYSBSG3006Z	T.SCREW	3	CB BKT+C.BASE	
	25	E47227-021	FOOT ASS'Y	2		
	26	QYSBSG3006Z	T.SCREW	2	FOOT ASS'Y+C.BASE	
	27	LV20960-001A	HEAT SINK	1		
	28	E73525-003SS	SCREW	10	TR	
	29	LV32433-001A	H.S BRACKET(R)	1		
	30	LV32434-001A	H.S BRACKET(L)	1		
	31	QYSBSG3008Z	T.SCREW	4	H.SINK BKT+H.SINK	
	32	QYSBSG3006Z	T.SCREW	2	H.SINK BKT+F.BKT	
	33	QYSBSG3006Z	T.SCREW	2	AMP M.C.B+H.SINK BKT	
	34	QYSBSG3006Z	T.SCREW	2	H.SINK BKT+C.BASE	
	35	QYSBSG3006Z	T.SCREW	3	A.M.C.B+C.B.&CB BKT	
	36	LV42098-001A	C.B BKT	1		
	37	QYSBSG3006Z	T.SCREW	1	C.B.BKT+C.BASE	
	38	QYSBSG3006Z	T.SCREW	3	T.C.B+C.BASE&F.BKT	
	39	QYSBSG3006Z	T.SCREW	1	P.CORD C.B+C.BASE	
	40	QQT0327-002	POWER TRANSF	1	T201	
	41	QYSDSTL4008Z	SPECIAL SCREW	4	P.TRANS	
	42	LV20961-006A	REAR PANEL	1	RX-E100RSB	
		LV20961-003A	REAR PANEL	1	RX-E100RSL	
	43	QYSBSGY3008M	SPECIAL SCREW	3	R.PANEL+C.BASE	
	44	QYSBSGY3008M	SPECIAL SCREW	1	R.PANEL+ud---	
	45	QYSBSGY3008M	SPECIAL SCREW	2	TUNER	
	46	QUQ412-2706CJ	FFC WIRE	1	I.M.C.B TO SCARRTE	

■ Parts list (General assembly)

Block No. M1MM

⚠	Item	Parts number	Parts name	Q'ty	Description	Area
⚠	47	QYSBSGY3008M	SPECIAL SCREW	5	SCART 2	
	48	QYSBSGY3008M	SPECIAL SCREW	1	SUB WOOFER	
	49	QYSBSGY3008M	SPECIAL SCREW	1	TAPE	
	50	QYSBSGY3008M	SPECIAL SCREW	5	SCART	
	51	QYSBSGY3008M	SPECIAL SCREW	2	DIGITAL	
	52	QYSBSGY3008M	SPECIAL SCREW	2	F.SPK TERM.+R.PANEL	
	53	QYSBSGY3008M	SPECIAL SCREW	2	R.SPK TERM.+R.PANEL	
	54	QYSBSG3006Z	T.SCREW	3	INPUT M.C.B+C.BASE	
	55	QMPN100-200-JD	POWER CORD	1		B
	56	QMPK150-200-JD	POWER CORD	1		E, EN
	57	QZW0033-001	STRAIN RELIEF	1		
	58	LV20962-001A/S/	TOP COVER	1		
	59	QYSBSGY3008M	SPECIAL SCREW	3		
	60	E406308-004	SPECIAL SCREW	4	RX-E100RSL	
	61	QMF51E2-1R6-J1	FUSE	1	F201	
	62	QMF51E2-2R0-J1	FUSE	2	F202 F203	
	63	QMF51E2-R10-J1	FUSE	1	F204	
	64	E307572-001	FASTENER	1		
	65	E409396-002	CAUTION LABEL	1		
	66	QYSBSG3008E	T.SCREW	1		
	67	LV30225-0C1A	FELT SPACER	2	FS400 FS401	
	68	QYSBSG3008E	T.SCREW	1		
	69	QYSBSG3008E	T.SCREW	2		
	70	QYSBSG3008E	T.SCREW	1		
	71	QYSBSG3008E	T.SCREW	2		

■ Electrical parts list (Power amp board)

Block No. 01

▲	Item	Parts number	Parts name	Remarks	Area
	C 201	QFLC2AJ-104Z	M CAPACITOR	.10MF 5% 100V	
	C 202	QFLC2AJ-104Z	M CAPACITOR	.10MF 5% 100V	
	C 203	QFLC2AJ-104Z	M CAPACITOR	.10MF 5% 100V	
	C 204	QETM1VM-228	E CAPACITOR	2200MF 20% 35V	
	C 205	QETM1VM-108	E CAPACITOR	1000MF 20% 35V	
	C 206	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 207	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 208	QFLC2AJ-472Z	M CAPACITOR	4700PF 5% 100V	
	C 209	QETN1EM-477Z	E CAPACITOR	470MF 20% 25V	
▲	C 210	QCZ9104-472	C CAPACITOR	4700PF	
	C 212	QETN1CM-477Z	E CAPACITOR	470MF 20% 16V	
	C 213	QETN0JM-228Z	E CAPACITOR	2200MF 20% 6.3V	
	C 214	QETN1HM-227Z	E CAPACITOR	220MF 20% 50V	
	C 215	QETN1JM-107Z	E CAPACITOR	100MF 20% 63V	
	C 216	QETN1HM-226Z	E CAPACITOR	22MF 20% 50V	
	C 217	QETN1HM-226Z	E CAPACITOR	22MF 20% 50V	
	C 218	QETN1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C 221	QETN1EM-107Z	E CAPACITOR	100MF 20% 25V	
	C 301	QETN1HM-225Z	E CAPACITOR	2.2MF 20% 50V	
	C 302	QETN1HM-225Z	E CAPACITOR	2.2MF 20% 50V	
	C 303	QCS31HJ-680Z	C CAPACITOR	68PF 5% 50V	
	C 304	QCS31HJ-680Z	C CAPACITOR	68PF 5% 50V	
	C 305	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 306	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 307	QCB31HK-152Z	C CAPACITOR	1500PF 10% 50V	
	C 308	QCB31HK-152Z	C CAPACITOR	1500PF 10% 50V	
	C 309	QETN1CM-107Z	E CAPACITOR	100MF 20% 16V	
	C 310	QETN1CM-107Z	E CAPACITOR	100MF 20% 16V	
	C 311	QCS31HJ-100Z	C CAPACITOR	10PF 5% 50V	
	C 312	QCS31HJ-100Z	C CAPACITOR	10PF 5% 50V	
	C 313	QFLC1HJ-103Z	M CAPACITOR	.010MF 5% 50V	
	C 314	QFLC1HJ-103Z	M CAPACITOR	.010MF 5% 50V	
	C 315	QCS32HJ-220Z	C CAPACITOR	22PF 5% 500V	
	C 316	QCS32HJ-220Z	C CAPACITOR	22PF 5% 500V	
	C 317	QETN1CM-107Z	E CAPACITOR	100MF 20% 16V	
	C 318	QETN1CM-107Z	E CAPACITOR	100MF 20% 16V	
	C 319	QETN1JM-107Z	E CAPACITOR	100MF 20% 63V	
	C 320	QETN1JM-107Z	E CAPACITOR	100MF 20% 63V	
	C 321	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 322	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 323	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 324	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 325	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 326	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 327	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 328	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 801	QETN1HM-225Z	E CAPACITOR	2.2MF 20% 50V	
	C 802	QETN1HM-225Z	E CAPACITOR	2.2MF 20% 50V	
	C 803	QCS31HJ-680Z	C CAPACITOR	68PF 5% 50V	
	C 804	QCS31HJ-680Z	C CAPACITOR	68PF 5% 50V	
	C 805	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 806	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 807	QCB31HK-152Z	C CAPACITOR	1500PF 10% 50V	
	C 808	QCB31HK-152Z	C CAPACITOR	1500PF 10% 50V	
	C 809	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C 810	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C 811	QCS31HJ-100Z	C CAPACITOR	10PF 5% 50V	
	C 812	QCS31HJ-100Z	C CAPACITOR	10PF 5% 50V	
	C 813	QFLC1HJ-103Z	M CAPACITOR	.010MF 5% 50V	
	C 814	QFLC1HJ-103Z	M CAPACITOR	.010MF 5% 50V	
	C 815	QCS32HJ-330Z	C CAPACITOR	33PF 5% 500V	
	C 816	QCS32HJ-330Z	C CAPACITOR	33PF 5% 500V	
	C 817	QETN1CM-107Z	E CAPACITOR	100MF 20% 16V	

▲	Item	Parts number	Parts name	Remarks	Area
	C 818	QETN1CM-107Z	E CAPACITOR	100MF 20% 16V	
	C 819	QETN2AM-106Z	E CAPACITOR	10MF 20% 100V	
	C 820	QETN2AM-106Z	E CAPACITOR	10MF 20% 100V	
	C 821	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 822	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 823	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 824	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 825	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 826	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 827	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 828	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 829	QETN1HM-476Z	E CAPACITOR	47MF 20% 50V	
	C 830	QETN1HM-476Z	E CAPACITOR	47MF 20% 50V	
	C 901	QETN1HM-225Z	E CAPACITOR	2.2MF 20% 50V	
	C 903	QCS31HJ-680Z	C CAPACITOR	68PF 5% 50V	
	C 905	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 907	QCB31HK-152Z	C CAPACITOR	1500PF 10% 50V	
	C 909	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C 911	QCS31HJ-100Z	C CAPACITOR	10PF 5% 50V	
	C 913	QFLC1HJ-103Z	M CAPACITOR	.010MF 5% 50V	
	C 915	QCS32HJ-330Z	C CAPACITOR	33PF 5% 500V	
	C 917	QETN1CM-107Z	E CAPACITOR	100MF 20% 16V	
	C 919	QETN2AM-106Z	E CAPACITOR	10MF 20% 100V	
	C 921	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 923	QCS32HJ-470Z	C CAPACITOR	47PF 5% 500V	
	C 925	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 927	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 929	QETN1HM-476Z	E CAPACITOR	47MF 20% 50V	
	CN201	QGD2501C1-05Z	SOCKET		
	CN204	QGF1205C1-12	CONNECTOR		
	CN207	WJK0037-001A	E-SI C WIRE C-B		
	CN217	QGA7901C1-02	CONNECTOR		
	CN701	QGB2510K1-09	CONNECTOR		
	CN702	QGB2510K1-09	CONNECTOR		
	CN703	QGB2510K1-09	CONNECTOR		
	CN704	QGB2510K1-09	CONNECTOR		
	CN705	QGB2510K1-09	CONNECTOR		
	CN707	QGD2501C1-04Z	SOCKET		
▲	D 201	10E2-FD	DIODE		
▲	D 202	1SR35-400A-T5	DIODE		
▲	D 203	10E2-FD	DIODE		
▲	D 204	1SR35-400A-T5	DIODE		
▲	D 206	1SR35-400A-T5	DIODE		
▲	D 207	1SR35-400A-T5	DIODE		
▲	D 208	1SR35-400A-T5	DIODE		
▲	D 209	1SR35-400A-T5	DIODE		
	D 210	1SS133-T2	SI DIODE		
	D 211	MTZJ6.2C-T2	Z DIODE		
	D 212	1SR35-400A-T5	DIODE		
▲	D 213	1SR35-400A-T5	DIODE		
▲	D 214	1SR35-400A-T5	DIODE		
▲	D 215	1SR35-400A-T5	DIODE		
	D 216	MTZJ27C-T2	Z DIODE		
	D 217	MTZJ6.2C-T2	Z DIODE		
	D 219	1SR35-400A-T5	DIODE		
	D 220	1SR35-400A-T5	DIODE		
	D 221	MTZJ6.2C-T2	Z DIODE		
	D 301	1SS133-T2	SI DIODE		
	D 302	1SS133-T2	SI DIODE		
	D 303	SLR-342MC-T	LED		
	D 304	SLR-342MC-T	LED		
	D 305	1SS133-T2	SI DIODE		
	D 306	1SS133-T2	SI DIODE		

■ Electrical parts list (Power amp board)

Block No. 01

△	Item	Parts number	Parts name	Remarks	Area
	D 307	1SS133-T2	SI DIODE		
	D 308	1SS133-T2	SI DIODE		
	D 309	1SS133-T2	SI DIODE		
	D 310	1SS133-T2	SI DIODE		
	D 801	1SS133-T2	SI DIODE		
	D 802	1SS133-T2	SI DIODE		
	D 805	1SS133-T2	SI DIODE		
	D 806	1SS133-T2	SI DIODE		
	D 807	1SS133-T2	SI DIODE		
	D 808	1SS133-T2	SI DIODE		
	D 809	1SS133-T2	SI DIODE		
	D 810	1SS133-T2	SI DIODE		
	D 901	1SS133-T2	SI DIODE		
	D 905	1SS133-T2	SI DIODE		
	D 907	1SS133-T2	SI DIODE		
	D 909	1SS133-T2	SI DIODE		
	EP201	QNZ0136-001Z	EARTH PLATE		
	EP202	E409182-001SM	GRAND TERMINAL		
	FC201	QNG0020-001Z	FUSE CLIP	(F201)	
	FC202	QNG0020-001Z	FUSE CLIP	(F201)	
	FC203	QNG0020-001Z	FUSE CLIP	(F202)	
	FC204	QNG0020-001Z	FUSE CLIP	(F202)	
	FC205	QNG0020-001Z	FUSE CLIP	(F203)	
	FC206	QNG0020-001Z	FUSE CLIP	(F203)	
	FC207	QNG0020-001Z	FUSE CLIP	(F204)	
	FC208	QNG0020-001Z	FUSE CLIP	(F204)	
	FW201	QUM135-22DGZ4	PARA RIBON WIRE		
	FW202	QJK017-031301	SIN CR C-B WIR		
	FW205	QUM134-22DGZ4	PARA RIBON WIRE		
	FW206	QUM133-08DGZ4	PARA RIBON WIRE		
	HS211	E70306-001	HEAT SINK		
	L 301	QQLZ005-R45	INDUCTOR		
	L 302	QQLZ005-R45	INDUCTOR		
	L 801	QQLZ005-R45	INDUCTOR		
	L 802	QQLZ005-R45	INDUCTOR		
	L 901	QQLZ005-R45	INDUCTOR		
	O 202	KRC105M-T	D TRANSISTOR		
	O 203	KTC3203/OY/-T	TRANSISTOR		
△	Q 204	KTA1046/Y/	TRANSISTOR		
	O 205	KTC3200/GL/-T	TRANSISTOR		
	O 207	KRC105M-T	D TRANSISTOR		
	O 208	KRC105M-T	D TRANSISTOR		
△	O 209	KRC105M-T	D TRANSISTOR		
	Q 211	2SD2395/EF/	TRANSISTOR		
	O 212	KRC105M-T	D TRANSISTOR		
	Q 301	2SC2240/L/-T	TRANSISTOR		
	O 302	2SC2240/L/-T	TRANSISTOR		
	O 303	2SC2240/L/-T	TRANSISTOR		
	Q 304	2SC2240/L/-T	TRANSISTOR		
	O 305	KTA1268/GL/-T	TRANSISTOR		
	O 306	KTA1268/GL/-T	TRANSISTOR		
	O 307	KTC3200/GL/-T	TRANSISTOR		
	O 308	KTC3200/GL/-T	TRANSISTOR		
	O 309	2SD637/QR/	TRANSISTOR		
	O 310	2SD637/QR/	TRANSISTOR		
	O 311	KTC3200/GL/-T	TRANSISTOR		
	O 312	KTC3200/GL/-T	TRANSISTOR		
	O 313	KTA1268/GL/-T	TRANSISTOR		
	O 314	KTA1268/GL/-T	TRANSISTOR		
△	O 315	2SD2389/OPY/-F6	TRANSISTOR		
△	O 316	2SD2389/OPY/-F6	TRANSISTOR		
△	O 317	2SB1559/OPY/-F6	TRANSISTOR		
△	O 318	2SB1559/OPY/-F6	TRANSISTOR		

△	Item	Parts number	Parts name	Remarks	Area
	O 319	KTA1268/GL/-T	TRANSISTOR		
	O 320	KTA1268/GL/-T	TRANSISTOR		
	O 801	2SC2240/L/-T	TRANSISTOR		
	O 802	2SC2240/L/-T	TRANSISTOR		
	Q 803	2SC2240/L/-T	TRANSISTOR		
	O 804	2SC2240/L/-T	TRANSISTOR		
	O 805	KTA1268/GL/-T	TRANSISTOR		
	O 806	KTA1268/GL/-T	TRANSISTOR		
	O 809	2SD637/QR/	TRANSISTOR		
	Q 810	2SD637/QR/	TRANSISTOR		
	O 811	KTC3200/GL/-T	TRANSISTOR		
	O 812	KTC3200/GL/-T	TRANSISTOR		
	O 813	KTA1268/GL/-T	TRANSISTOR		
	O 814	KTA1268/GL/-T	TRANSISTOR		
△	O 815	2SD2389/OPY/-F6	TRANSISTOR		
△	O 816	2SD2389/OPY/-F6	TRANSISTOR		
△	O 817	2SB1559/OPY/-F6	TRANSISTOR		
△	O 818	2SB1559/OPY/-F6	TRANSISTOR		
	O 819	KTA1268/GL/-T	TRANSISTOR		
	O 820	KTA1268/GL/-T	TRANSISTOR		
	O 901	2SC2240/L/-T	TRANSISTOR		
	O 903	2SC2240/L/-T	TRANSISTOR		
	O 905	KTA1268/GL/-T	TRANSISTOR		
	O 909	2SD637/QR/	TRANSISTOR		
	O 911	KTC3200/GL/-T	TRANSISTOR		
	O 913	KTA1268/GL/-T	TRANSISTOR		
△	O 915	2SD2389/OPY/-F6	TRANSISTOR		
△	O 917	2SB1559/OPY/-F6	TRANSISTOR		
	O 919	KTA1268/GL/-T	TRANSISTOR		
△	R 201	QRJ146J-5R6X	UNF C RESISTOR	5.6 5% 1/4W	
△	R 202	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 203	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 204	QRJ146J-821X	UNF C RESISTOR	820 5% 1/4W	
△	R 206	QRJ146J-332X	UNF C RESISTOR	3.3K 5% 1/4W	
	R 207	QRE141J-223Y	C RESISTOR	22K 5% 1/4W	
△	R 208	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
	R 209	QRE141J-104Y	C RESISTOR	100K 5% 1/4W	
△	R 211	QRZ9005-120X	F RESISTOR	12 1/0W	
△	R 212	QRJ146J-682X	UNF C RESISTOR	6.8K 5% 1/4W	
	R 213	QRE141J-331Y	C RESISTOR	330 5% 1/4W	
△	R 214	QRJ146J-120X	UNF C RESISTOR	12 5% 1/4W	
	R 301	QRE141J-222Y	C RESISTOR	2.2K 5% 1/4W	
	R 302	QRE141J-222Y	C RESISTOR	2.2K 5% 1/4W	
	R 303	QRE141J-683Y	C RESISTOR	68K 5% 1/4W	
	R 304	QRE141J-683Y	C RESISTOR	68K 5% 1/4W	
	R 305	QRE141J-123Y	C RESISTOR	12K 5% 1/4W	
	R 306	QRE141J-123Y	C RESISTOR	12K 5% 1/4W	
	R 307	QRE141J-202Y	C RESISTOR	2.0K 5% 1/4W	
	R 308	QRE141J-202Y	C RESISTOR	2.0K 5% 1/4W	
	R 309	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 310	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
△	R 311	QRJ146J-391X	UNF C RESISTOR	390 5% 1/4W	
△	R 312	QRJ146J-391X	UNF C RESISTOR	390 5% 1/4W	
	R 313	QRE141J-563Y	C RESISTOR	56K 5% 1/4W	
	R 314	QRE141J-563Y	C RESISTOR	56K 5% 1/4W	
△	R 315	QRJ146J-121X	UNF C RESISTOR	120 5% 1/4W	
△	R 316	QRJ146J-121X	UNF C RESISTOR	120 5% 1/4W	
	R 317	QRE141J-473Y	C RESISTOR	47K 5% 1/4W	
	R 318	QRE141J-473Y	C RESISTOR	47K 5% 1/4W	
△	R 319	QRJ146J-471X	UNF C RESISTOR	470 5% 1/4W	
△	R 320	QRJ146J-471X	UNF C RESISTOR	470 5% 1/4W	
△	R 321	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 322	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	

■ Electrical parts list (Power amp board)

Block No. 01

△	Item	Parts number	Parts name	Remarks	Area
△	R 323	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 324	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
	R 325	QRE141J-361Y	C RESISTOR	360 5% 1/4W	
	R 326	QRE141J-361Y	C RESISTOR	360 5% 1/4W	
	R 327	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 328	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 329	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 330	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
△	R 331	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 332	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 333	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 334	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
	R 335	QRE141J-820Y	C RESISTOR	82 5% 1/4W	
	R 336	QRE141J-820Y	C RESISTOR	82 5% 1/4W	
	R 337	QRE141J-820Y	C RESISTOR	82 5% 1/4W	
	R 338	QRE141J-820Y	C RESISTOR	82 5% 1/4W	
	R 339	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 340	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 341	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 342	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 343	QRZ0218-R22	EMIT RESISTOR	1/2W	
	R 344	QRZ0218-R22	EMIT RESISTOR	1/2W	
	R 345	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 346	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 347	QRE141J-153Y	C RESISTOR	15K 5% 1/4W	
	R 348	QRE141J-153Y	C RESISTOR	15K 5% 1/4W	
	R 349	QRE141J-473Y	C RESISTOR	47K 5% 1/4W	
	R 350	QRE141J-473Y	C RESISTOR	47K 5% 1/4W	
△	R 351	QRJ125J-330	UNF C RESISTOR	33 5% 1/2W	
△	R 352	QRJ125J-330	UNF C RESISTOR	33 5% 1/2W	
△	R 353	QRL022J-100	UNF OMF RESISTOR	10 5% 1/2W	
△	R 354	QRL022J-100	UNF OMF RESISTOR	10 5% 1/2W	
	R 801	QRE141J-222Y	C RESISTOR	2.2K 5% 1/4W	
	R 802	QRE141J-222Y	C RESISTOR	2.2K 5% 1/4W	
	R 803	QRE141J-563Y	C RESISTOR	56K 5% 1/4W	
	R 804	QRE141J-563Y	C RESISTOR	56K 5% 1/4W	
	R 805	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 806	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 807	QRE141J-302Y	C RESISTOR	3.0K 5% 1/4W	
	R 808	QRE141J-302Y	C RESISTOR	3.0K 5% 1/4W	
	R 809	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 810	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
△	R 811	QRJ146J-391X	UNF C RESISTOR	390 5% 1/4W	
△	R 812	QRJ146J-391X	UNF C RESISTOR	390 5% 1/4W	
	R 813	QRE141J-563Y	C RESISTOR	56K 5% 1/4W	
	R 814	QRE141J-563Y	C RESISTOR	56K 5% 1/4W	
△	R 815	QRJ146J-221X	UNF C RESISTOR	220 5% 1/4W	
△	R 816	QRJ146J-221X	UNF C RESISTOR	220 5% 1/4W	
△	R 821	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 822	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 823	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 824	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
	R 825	QRE141J-361Y	C RESISTOR	360 5% 1/4W	
	R 826	QRE141J-361Y	C RESISTOR	360 5% 1/4W	
	R 827	QRE141J-751Y	C RESISTOR	750 5% 1/4W	
	R 828	QRE141J-751Y	C RESISTOR	750 5% 1/4W	
	R 829	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
	R 830	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
△	R 831	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 832	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 833	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 834	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
	R 835	QRE141J-101Y	C RESISTOR	100 5% 1/4W	

△	Item	Parts number	Parts name	Remarks	Area
	R 836	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 837	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 838	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 839	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 840	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 841	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 842	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 843	QRZ0218-R22	EMIT RESISTOR	1/2W	
	R 844	QRZ0218-R22	EMIT RESISTOR	1/2W	
	R 845	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 846	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 847	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 848	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 849	QRE141J-123Y	C RESISTOR	12K 5% 1/4W	
	R 850	QRE141J-123Y	C RESISTOR	12K 5% 1/4W	
△	R 851	QRJ125J-330	UNF C RESISTOR	33 5% 1/2W	
△	R 852	QRJ125J-330	UNF C RESISTOR	33 5% 1/2W	
△	R 853	QRL022J-100	UNF OMF RESISTOR	10 5% 1/2W	
△	R 854	QRL022J-100	UNF OMF RESISTOR	10 5% 1/2W	
	R 855	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 856	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 857	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 858	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 859	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 860	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 861	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 862	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 901	QRE141J-222Y	C RESISTOR	2.2K 5% 1/4W	
	R 903	QRE141J-563Y	C RESISTOR	56K 5% 1/4W	
	R 905	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 907	QRE141J-302Y	C RESISTOR	3.0K 5% 1/4W	
	R 909	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
△	R 911	QRJ146J-391X	UNF C RESISTOR	390 5% 1/4W	
	R 913	QRE141J-563Y	C RESISTOR	56K 5% 1/4W	
△	R 915	QRJ146J-221X	UNF C RESISTOR	220 5% 1/4W	
△	R 921	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 923	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
	R 925	QRE141J-361Y	C RESISTOR	360 5% 1/4W	
	R 927	QRE141J-751Y	C RESISTOR	750 5% 1/4W	
	R 929	QRE141J-471Y	C RESISTOR	470 5% 1/4W	
△	R 931	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
△	R 933	QRJ146J-100X	UNF C RESISTOR	10 5% 1/4W	
	R 935	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 937	QRE141J-101Y	C RESISTOR	100 5% 1/4W	
	R 939	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 941	QRE141J-181Y	C RESISTOR	180 5% 1/4W	
	R 943	QRZ0218-R22	EMIT RESISTOR	1/2W	
	R 945	QRE141J-102Y	C RESISTOR	1.0K 5% 1/4W	
	R 947	QRE141J-183Y	C RESISTOR	18K 5% 1/4W	
	R 949	QRE141J-473Y	C RESISTOR	47K 5% 1/4W	
△	R 951	QRJ125J-330	UNF C RESISTOR	33 5% 1/2W	
△	R 953	QRL022J-100	UNF OMF RESISTOR	10 5% 1/2W	
	R 955	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 957	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 959	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
	R 961	QRE141J-332Y	C RESISTOR	3.3K 5% 1/4W	
△	RY201	QSK0055-001	RELAY		
△	T 202	QQT0281-002	POWER TRANSF		
	TA201	QNZ0079-001Z	TAB		
	TA202	QNZ0079-001Z	TAB		
△	TH201	QAD0095-4R7Z	POSISTOR		
△	TH301	QAD0012-202	THERMISTOR		
△	TH302	QAD0012-202	THERMISTOR		
△	TH801	QAD0012-202	THERMISTOR		
△	TH802	QAD0012-202	THERMISTOR		
△	TH901	QAD0012-202	THERMISTOR		
	VR301	QVP0008-102Z	SEMI V RESISTOR		
	VR302	QVP0008-102Z	SEMI V RESISTOR		

■ Electrical parts list (Main & System control board) Block No. 02

△	Item	Parts number	Parts name	Remarks	Area
	BK401	LV32554-001A	FL HOLDER(L)		
	BK402	LV32555-001A	FL HOLDER(R)		
	C 401	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 402	NCB31CK-223X	C CAPACITOR		
	C 403	QETN1HM-225Z	E CAPACITOR	2.2MF 20% 50V	
	C 404	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 405	QCZ0205-155Z	ML C CAPACITOR	1.5MF	
	C 406	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 407	QEK1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 408	QEK1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 409	NCB31HK-102X	C CAPACITOR		
	C 410	NCB31HK-102X	C CAPACITOR		
	C 411	NCB31HK-102X	C CAPACITOR		
	C 412	NCB31HK-103X	C CAPACITOR		
	C 413	NCB31HK-103X	C CAPACITOR		
	C 414	NCB31HK-103X	C CAPACITOR		
	C 415	NCB31HK-103X	C CAPACITOR		
	C 416	NCB31HK-103X	C CAPACITOR		
	C 417	NCB31HK-561X	C CAPACITOR		
	C 418	NCB31CK-223X	C CAPACITOR		
	C 701	QFZ9076-104Z	MM CAPACITOR	.10MF	
	C 702	QFZ9076-104Z	MM CAPACITOR	.10MF	
	C 703	QFZ9076-104Z	MM CAPACITOR	.10MF	
	C 704	QTE1J45-478	E CAPACITOR		
	C 705	QTE1J45-478	E CAPACITOR		
	C 706	QETN1EM-476Z	E CAPACITOR	47MF 20% 25V	
	C 709	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C 710	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C 711	QEK1HM-226Z	E CAPACITOR	22MF 20% 50V	
	C 712	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 713	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 714	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 715	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 717	QCS31HJ-101Z	C CAPACITOR	100PF 5% 50V	
	C 741	QFLC1HJ-223Z	M CAPACITOR	.022MF 5% 50V	
	C 742	QFLC1HJ-223Z	M CAPACITOR	.022MF 5% 50V	
	C 743	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 744	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 745	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 746	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 747	QCF31HZ-223Z	C CAPACITOR	.022MF +80:-20%	
	C 748	QCF31HZ-223Z	C CAPACITOR	.022MF +80:-20%	
	C 749	QFLC1HJ-223Z	M CAPACITOR	.022MF 5% 50V	
	C 750	QFLC1HJ-223Z	M CAPACITOR	.022MF 5% 50V	
	C 751	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 752	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 753	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 754	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 755	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 756	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 757	QFLC1HJ-473Z	M CAPACITOR	.047MF 5% 50V	
	C 758	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 759	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	C 760	QCS31HJ-221Z	C CAPACITOR	220PF 5% 50V	
	CL701	QZW0038-001	WIRE CLAMP		
	CL702	QZW0038-001	WIRE CLAMP		
	CN121	QGB2501J1-12	CONNECTOR		
	CN122	QGB2501J1-04	CONNECTOR		
	CN202	QGA2501C1-03	3P CONNECTOR		
	CN206	QGD2501C1-03Z	SOCKET		
	CN214	QGF1205F1-12	CONNECTOR		
	CN401	QGF1205F1-17	CONNECTOR		
	CN402	QGF1205F1-14	CONNECTOR		

△	Item	Parts number	Parts name	Remarks	Area
	CN513	QGB2510K1-12	CONNECTOR		
	CN514	QGB2510K1-04	CONNECTOR		
	CN515	QGA2501C1-03	3P CONNECTOR		
	CN516	QGA2501C1-02	2P CONNECTOR		
	CN517	QGA2501C1-03	3P CONNECTOR		
	CN711	QGB2510J1-09	CONNECTOR		
	CN712	QGB2510J1-09	CONNECTOR		
	CN713	QGB2510J1-09	CONNECTOR		
	CN714	QGB2510J1-09	CONNECTOR		
	CN715	QGB2510J1-09	CONNECTOR		
	D 401	SLR-342MC-T	LED		
	D 402	SLR-342MC-T	LED		
	D 403	SLR-342MC-T	LED		
	D 404	SPR-325MVW/L/-T	LED		
	D 405	SPR-325MVW/L/-T	LED		
	D 406	SPR-325MVW/L/-T	LED		
	D 407	SLR-342VC-T	LED		
	D 408	1SS355-X	DIODE		
△	D 701	30DF2-FC	DIODE		
△	D 702	30DF2-FC	DIODE		
△	D 703	30DF2-FC	DIODE		
△	D 704	30DF2-FC	DIODE		
	D 705	MTZJ18C-T2	Z DIODE		
	D 707	1SS133-T2	SI DIODE		
	D 708	1SS133-T2	SI DIODE		
	D 709	MTZJ15C-T2	Z DIODE		
	D 710	MTZJ5.1C-T2	Z DIODE		
	D 711	1SS133-T2	SI DIODE		
	D 712	1SS133-T2	SI DIODE		
	D 713	1SS133-T2	SI DIODE		
	D 714	1SS133-T2	SI DIODE		
	D 715	1SS133-T2	SI DIODE		
	D 716	1SS133-T2	SI DIODE		
	D 741	1SS133-T2	SI DIODE		
	D 742	1SS133-T2	SI DIODE		
	D 743	1SS133-T2	SI DIODE		
	DI401	QLF0086-001	FL TUBE		
	EP701	QNZ0136-001Z	EARTH PLATE		
	FW401	QUM133-20Z4Z4	PARA RIBON WIRE		
	FW701	QUM134-27Z4Z4	PARA RIBON WIRE		
	FW702	QUM136-24Z4Z4	PARA RIBON WIRE		
	FW707	QUM134-22DGZ4	PARA RIBON WIRE		
	IC401	MN101C35DHR	IC		
	IC402	BU2092F-X	IC		
	IC403	GP1U281X	IC		
	IC404	IC-PST9139-T	IC		
	L 741	QQLZ005-R45	INDUCTOR		
	L 742	QQLZ005-R45	INDUCTOR		
	L 743	QQLZ005-R45	INDUCTOR		
	L 744	QQLZ005-R45	INDUCTOR		
	L 745	QQLZ005-R45	INDUCTOR		
	O 401	KTC3199/GL/-T	TRANSISTOR		
	O 402	KTC3199/GL/-T	TRANSISTOR		
	O 403	KTC3199/GL/-T	TRANSISTOR		
	O 404	KTC3199/GL/-T	TRANSISTOR		
	O 405	KTC3199/GL/-T	TRANSISTOR		
	O 406	KTC3199/GL/-T	TRANSISTOR		
	O 407	DTC114EKA-X	TRANSISTOR		
	O 408	DTA114EKA-X	D TRANSISTOR		
	O 409	DTA114EKA-X	D TRANSISTOR		
	O 410	DTA114EKA-X	D TRANSISTOR		
	O 411	DTA114EKA-X	D TRANSISTOR		
	O 412	DTA114EKA-X	D TRANSISTOR		

■ Electrical parts list (Main & System control board) Block No. 02

▲	Item	Parts number	Parts name	Remarks	Area	▲	Item	Parts number	Parts name	Remarks	Area
	O 413	DTA114EKA-X	D TRANSISTOR				R 448	NRSA63J-152X	MG RESISTOR		
	O 702	KTC3200/GL/-T	TRANSISTOR				R 449	NRSA63J-222X	MG RESISTOR		
	O 703	KTA1268/GL/-T	TRANSISTOR				R 450	NRSA63J-272X	MG RESISTOR		
	O 704	KTC3199/GL/-T	TRANSISTOR				R 451	NRSA63J-392X	MG RESISTOR		
	Q 705	2SD2395/EF/	TRANSISTOR				R 452	NRSA63J-103X	MG RESISTOR		
	O 706	KTA1023/OY/-T	TRANSISTOR				R 453	NRSA63J-102X	MG RESISTOR		
	O 707	KTC3200/GL/-T	TRANSISTOR				R 454	NRSA63J-102X	MG RESISTOR		
	O 708	KRC109M-T	D TRANSISTOR				R 455	NRSA63J-103X	MG RESISTOR		
	O 709	KRC109M-T	D TRANSISTOR				R 456	NRSA63J-103X	MG RESISTOR		
	Q 710	KRC109M-T	D TRANSISTOR				R 464	NRSA63J-221X	MG RESISTOR		
	O 711	KRC109M-T	D TRANSISTOR				R 465	NRSA63J-221X	MG RESISTOR		
	O 712	KRC109M-T	D TRANSISTOR				R 466	NRSA63J-221X	MG RESISTOR		
	O 713	KRC109M-T	D TRANSISTOR				R 467	NRSA63J-221X	MG RESISTOR		
	O 714	KRC109M-T	D TRANSISTOR				R 468	NRSA63J-221X	MG RESISTOR		
	O 715	KRC109M-T	D TRANSISTOR				R 469	NRSA63J-221X	MG RESISTOR		
	R 400	NRSA63J-103X	MG RESISTOR				R 470	NRSA63J-221X	MG RESISTOR		
	R 401	NRSA63J-223X	MG RESISTOR				R 471	NRSA63J-221X	MG RESISTOR		
	R 402	NRSA63J-473X	MG RESISTOR				R 472	NRSA63J-221X	MG RESISTOR		
	R 403	NRSA63J-683X	MG RESISTOR				R 473	NRSA63J-221X	MG RESISTOR		
	R 404	NRSA63J-473X	MG RESISTOR				R 474	NRSA63J-221X	MG RESISTOR		
	R 405	NRSA63J-153X	MG RESISTOR				R 475	NRSA63J-221X	MG RESISTOR		
	R 406	NRSA63J-273X	MG RESISTOR				R 476	NRSA63J-221X	MG RESISTOR		
	R 407	NRSA63J-103X	MG RESISTOR				R 477	NRSA63J-221X	MG RESISTOR		
	R 408	NRSA63J-103X	MG RESISTOR				R 478	NRSA63J-221X	MG RESISTOR		
	R 409	NRSA63J-473X	MG RESISTOR				R 479	NRSA63J-221X	MG RESISTOR		
	R 410	NRSA63J-473X	MG RESISTOR				R 480	NRSA63J-221X	MG RESISTOR		
	R 411	NRSA63J-683X	MG RESISTOR				R 488	NRSA63J-103X	MG RESISTOR		
	R 412	NRSA63J-473X	MG RESISTOR				R 489	NRSA63J-103X	MG RESISTOR		
	R 413	NRSA63J-153X	MG RESISTOR				R 490	NRSA63J-103X	MG RESISTOR		
	R 414	NRSA63J-273X	MG RESISTOR				R 491	NRSA63J-221X	MG RESISTOR		
	R 415	NRSA63J-103X	MG RESISTOR				R 492	NRSA63J-392X	MG RESISTOR		
	R 416	NRSA63J-103X	MG RESISTOR				R 493	NRSA63J-103X	MG RESISTOR		
	R 417	NRSA63J-223X	MG RESISTOR				R 494	NRSA63J-103X	MG RESISTOR		
	R 418	NRSA63J-473X	MG RESISTOR				R 495	NRSA63J-103X	MG RESISTOR		
	R 419	NRSA63J-683X	MG RESISTOR				R 496	NRSA63J-103X	MG RESISTOR		
	R 420	NRSA63J-473X	MG RESISTOR				R 497	NRSA63J-103X	MG RESISTOR		
	R 421	NRSA63J-153X	MG RESISTOR				R 498	NRSA63J-103X	MG RESISTOR		
	R 422	NRSA63J-273X	MG RESISTOR				R 499	NRSA63J-103X	MG RESISTOR		
	R 423	NRSA63J-103X	MG RESISTOR			▲	R 701	QRL022J-562	UNF OMF RESISTOR	5.6K 5% 1/2W	
	R 424	NRSA63J-103X	MG RESISTOR				R 704	NRSA63J-104X	MG RESISTOR		
	R 425	NRSA63J-103X	MG RESISTOR				R 705	NRSA63J-104X	MG RESISTOR		
	R 426	NRSA63J-223X	MG RESISTOR				R 706	NRSA63J-823X	MG RESISTOR		
	R 427	NRSA63J-472X	MG RESISTOR				R 707	NRSA63J-104X	MG RESISTOR		
	R 428	NRSA63J-221X	MG RESISTOR				R 708	NRSA63J-823X	MG RESISTOR		
	R 429	NRSA63J-103X	MG RESISTOR				R 709	NRSA63J-103X	MG RESISTOR		
	R 430	NRSA63J-102X	MG RESISTOR				R 710	NRSA63J-103X	MG RESISTOR		
	R 431	NRSA63J-102X	MG RESISTOR				R 711	NRSA63J-104X	MG RESISTOR		
	R 432	NRSA63J-122X	MG RESISTOR				R 712	NRSA63J-104X	MG RESISTOR		
	R 433	NRSA63J-152X	MG RESISTOR			▲	R 713	QRZ9005-100X	F RESISTOR	10 1/0W	
	R 434	NRSA63J-222X	MG RESISTOR			▲	R 714	QRJ146J-103X	UNF C RESISTOR	10K 5% 1/4W	
	R 435	NRSA63J-272X	MG RESISTOR			▲	R 715	QRZ9005-100X	F RESISTOR	10 1/0W	
	R 436	NRSA63J-103X	MG RESISTOR			▲	R 716	QRJ146J-102X	UNF C RESISTOR	1.0K 5% 1/4W	
	R 437	NRSA63J-102X	MG RESISTOR			▲	R 717	QRJ146J-223X	UNF C RESISTOR	22K 5% 1/4W	
	R 438	NRSA63J-102X	MG RESISTOR				R 718	NRSA63J-103X	MG RESISTOR		
	R 439	NRSA63J-122X	MG RESISTOR				R 719	NRSA63J-473X	MG RESISTOR		
	R 440	NRSA63J-152X	MG RESISTOR			▲	R 720	QRJ146J-392X	UNF C RESISTOR	3.9K 5% 1/4W	
	R 441	NRSA63J-222X	MG RESISTOR				R 721	NRSA63J-472X	MG RESISTOR		
	R 442	NRSA63J-272X	MG RESISTOR				R 722	NRSA63J-223X	MG RESISTOR		
	R 443	NRSA63J-392X	MG RESISTOR				R 723	NRSA63J-153X	MG RESISTOR		
	R 444	NRSA63J-103X	MG RESISTOR				R 724	NRSA63J-472X	MG RESISTOR		
	R 445	NRSA63J-102X	MG RESISTOR				R 725	NRSA63J-472X	MG RESISTOR		
	R 446	NRSA63J-102X	MG RESISTOR				R 726	NRSA63J-472X	MG RESISTOR		
	R 447	NRSA63J-122X	MG RESISTOR				R 727	NRSA63J-472X	MG RESISTOR		

■ Electrical parts list (Main & System control board) Block No. 02

△	Item	Parts number	Parts name	Remarks	Area
	R 728	NRSA63J-472X	MG RESISTOR		
	R 729	NRSA63J-223X	MG RESISTOR		
	R 730	NRSA63J-153X	MG RESISTOR		
	R 731	NRSA63J-223X	MG RESISTOR		
	R 732	NRSA63J-153X	MG RESISTOR		
△	R 741	QRJ146J-120X	UNF C RESISTOR	12 5% 1/4W	
△	R 742	QRJ146J-120X	UNF C RESISTOR	12 5% 1/4W	
△	R 743	QRJ146J-120X	UNF C RESISTOR	12 5% 1/4W	
△	R 745	QRJ146J-3R9X	UNF C RESISTOR	3.9 5% 1/4W	
△	R 746	QRJ146J-3R9X	UNF C RESISTOR	3.9 5% 1/4W	
△	R 747	QRJ146J-3R9X	UNF C RESISTOR	3.9 5% 1/4W	
△	R 748	QRJ146J-3R9X	UNF C RESISTOR	3.9 5% 1/4W	
△	R 749	QRJ146J-3R9X	UNF C RESISTOR	3.9 5% 1/4W	
△	RY701	QSK0082-001	RELAY		
△	RY741	QSK0109-001	RELAY		
△	RY742	QSK0109-001	RELAY		
△	RY743	QSK0109-001	RELAY		
	R1422	NRSA63J-104X	MG RESISTOR		
	R1431	NRSA63J-221X	MG RESISTOR		
	R1432	NRSA63J-221X	MG RESISTOR		
	R1433	NRSA63J-221X	MG RESISTOR		
	S 401	QSW0683-001Z	PUSH SWITCH	SURROUND	
	S 402	QSW0683-001Z	PUSH SWITCH	DSP MODE	
	S 403	QSW0683-001Z	PUSH SWITCH	INPUT MODE	
	S 404	QSW0683-001Z	PUSH SWITCH	DVD	
	S 405	QSW0683-001Z	PUSH SWITCH	STB	
	S 406	QSW0683-001Z	PUSH SWITCH	UP	
	S 407	QSW0683-001Z	PUSH SWITCH	LEFT	
	S 408	QSW0683-001Z	PUSH SWITCH	VOL.DOWN	
	S 409	QSW0683-001Z	PUSH SWITCH	ADJUST	
	S 410	QSW0683-001Z	PUSH SWITCH	SETTING	
	S 411	QSW0683-001Z	PUSH SWITCH	VCR	
	S 412	QSW0683-001Z	PUSH SWITCH	TV	
	S 413	QSW0683-001Z	PUSH SWITCH	DOWN	
	S 414	QSW0683-001Z	PUSH SWITCH	RIGHT	
	S 415	QSW0683-001Z	PUSH SWITCH	VOL.UP	
	S 416	QSW0683-001Z	PUSH SWITCH	MEMORY	
	S 417	QSW0683-001Z	PUSH SWITCH	TAPE	
	S 418	QSW0683-001Z	PUSH SWITCH	FM/AM	
	S 421	QSW0683-001Z	PUSH SWITCH	POWER	
	S 422	QSW0683-001Z	PUSH SWITCH	AMP/SWITCH	
	ST741	QNB0082-001	SPK TERMINAL	FRONT	
	ST742	QNB0016-001	SPK TERMINAL	CNT/SR	
	X 401	QAX0246-001Z	RESONATOR		

■ Electrical parts list (Audio signal input board)

Block No. 03

▲	Item	Parts number	Parts name	Remarks	Area
	C 501	NCS31HJ-331X	C CAPACITOR		
	C 502	NCS31HJ-331X	C CAPACITOR		
	C 503	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 504	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 505	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 506	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 507	NCS31HJ-331X	C CAPACITOR		
	C 508	NCS31HJ-331X	C CAPACITOR		
	C 509	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 510	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 511	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 512	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 513	NCS31HJ-331X	C CAPACITOR		
	C 514	NCS31HJ-331X	C CAPACITOR		
	C 515	NCS31HJ-221X	C CAPACITOR		
	C 516	NCS31HJ-221X	C CAPACITOR		
	C 517	NCS31HJ-331X	C CAPACITOR		
	C 518	NCS31HJ-331X	C CAPACITOR		
	C 519	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 520	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 521	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C 522	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C 523	QFLC1HJ-683Z	M CAPACITOR	.068MF 5% 50V	
	C 524	QFLC1HJ-683Z	M CAPACITOR	.068MF 5% 50V	
	C 525	QFLC1HJ-682Z	M CAPACITOR	6800PF 5% 50V	
	C 526	QFLC1HJ-682Z	M CAPACITOR	6800PF 5% 50V	
	C 527	QFLC1HJ-682Z	M CAPACITOR	6800PF 5% 50V	
	C 528	QFLC1HJ-682Z	M CAPACITOR	6800PF 5% 50V	
	C 529	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 530	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 531	QFLC1HJ-104Z	M CAPACITOR	.10MF 5% 50V	
	C 532	QFLC1HJ-104Z	M CAPACITOR	.10MF 5% 50V	
	C 533	QFLC1HJ-104Z	M CAPACITOR	.10MF 5% 50V	
	C 534	QFLC1HJ-104Z	M CAPACITOR	.10MF 5% 50V	
	C 535	NCB31CK-223X	C CAPACITOR		
	C 536	NCB31CK-223X	C CAPACITOR		
	C 537	NCB31CK-223X	C CAPACITOR		
	C 541	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 542	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 544	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 545	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 546	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 549	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 550	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 551	QFLC1HJ-562Z	M CAPACITOR	5600PF 5% 50V	
	C 552	QFLC1HJ-562Z	M CAPACITOR	5600PF 5% 50V	
	C 553	QETN0JM-477Z	E CAPACITOR	470MF 20% 6.3V	
	C 554	QETN1HM-225Z	E CAPACITOR	2.2MF 20% 50V	
	C 555	NCB31CK-223X	C CAPACITOR		
	C 556	NCB31CK-223X	C CAPACITOR		
	C 557	QETN1EM-476Z	E CAPACITOR	47MF 20% 25V	
	C 558	QETN1EM-476Z	E CAPACITOR	47MF 20% 25V	
	C 559	QETN1EM-476Z	E CAPACITOR	47MF 20% 25V	
	C 560	QETN1EM-107Z	E CAPACITOR	100MF 20% 25V	
	C 561	QETN1EM-107Z	E CAPACITOR	100MF 20% 25V	
	C 562	QETN1EM-107Z	E CAPACITOR	100MF 20% 25V	
	C 563	QCZ0205-155Z	ML C CAPACITOR	1.5MF	
	C 564	QCF31HZ-223Z	C CAPACITOR	.022MF +80:-20%	
	C 565	QETN1EM-107Z	E CAPACITOR	100MF 20% 25V	
	C 566	QETN1EM-107Z	E CAPACITOR	100MF 20% 25V	
	C 577	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C 578	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C 581	QETN1HM-225Z	E CAPACITOR	2.2MF 20% 50V	

▲	Item	Parts number	Parts name	Remarks	Area
	C 591	NCS31HJ-220X	C CAPACITOR		
	C 592	NCS31HJ-220X	C CAPACITOR		
	C 601	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C 602	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C 603	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 604	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 605	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C 606	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	CL501	QZW0038-001	WIRE CLAMP		
	CL502	QZW0038-001	WIRE CLAMP		
	CN205	QGD2501C1-04Z	SOCKET		
	CN411	QGF1205C1-17	CONNECTOR		
	CN412	QGF1205F1-14	CONNECTOR		
	CN501	QGB2510J1-20	CONNECTOR		
	CN502	QGF1205C1-27	CONNECTOR		
	CN503	QGB2510J1-12	CONNECTOR		
	CN504	QGB2510J1-04	CONNECTOR		
	CN505	QJP001-031401	SHI CR C-B WIRE		
	CN506	QJP002-021401	SHI CR C-B WIRE		
	CN507	QJP001-031101	SHI CR C-B WIRE		
	CN508	QJQ007-031201	SKT WIRE ASSY		
	CN511	QGB2510K1-20	B TO B CONNE		
	CN512	QGF1205F1-27	CONNECTOR		
	CN601	QGB2510J1-20	CONNECTOR		
	C1505	NCS31HJ-331X	C CAPACITOR		
	C1506	NCS31HJ-331X	C CAPACITOR		
	C1507	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C1508	NCS31HJ-470X	C CAPACITOR		
	C1509	QETN0JM-477Z	E CAPACITOR	470MF 20% 6.3V	
	C1510	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C1515	NCS31HJ-331X	C CAPACITOR		
	C1516	NCS31HJ-331X	C CAPACITOR		
	C1517	NCS31HJ-470X	C CAPACITOR		
	C1518	QETN0JM-477Z	E CAPACITOR	470MF 20% 6.3V	
	C1519	NCS31HJ-470X	C CAPACITOR		
	C1520	QETN0JM-477Z	E CAPACITOR	470MF 20% 6.3V	
	C1521	NCS31HJ-470X	C CAPACITOR		
	C1522	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C1523	NCS31HJ-470X	C CAPACITOR		
	C1524	QETN0JM-477Z	E CAPACITOR	470MF 20% 6.3V	
	C1528	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C1529	QCZ0205-155Z	ML C CAPACITOR	1.5MF	
	C1536	QETN0JM-477Z	E CAPACITOR	470MF 20% 6.3V	
	C1538	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C1539	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C1540	NCS31HJ-470X	C CAPACITOR		
	C1541	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C1542	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C1543	NCB31CK-223X	C CAPACITOR		
	C1544	NCB31CK-223X	C CAPACITOR		
	D 503	MTZJ7.5C-T2	Z DIODE		
	D 504	MTZJ7.5C-T2	Z DIODE		
	D 505	MTZJ15C-T2	Z DIODE		
	D 506	MTZJ15C-T2	Z DIODE		
	D 507	MTZJ5.6C-T2	Z DIODE		
	D 508	MTZJ5.6C-T2	Z DIODE		
	D 509	1SS355-X	DIODE		
	D 511	MTZJ13C-T2	Z DIODE		
	D 512	MTZJ13C-T2	Z DIODE		
	D 513	MTZJ13C-T2	Z DIODE		
	D 514	MTZJ13C-T2	Z DIODE		
	D 515	MTZJ13C-T2	Z DIODE		
	D 516	MTZJ13C-T2	Z DIODE		

■ Electrical parts list (Audio signal input board)

Block No. 03

△	Item	Parts number	Parts name	Remarks	Area
	D 517	MTZJ13C-T2	Z DIODE		
	D 518	MTZJ13C-T2	Z DIODE		
	D 519	MTZJ10C-T2	Z DIODE		
	D 520	MTZJ13C-T2	Z DIODE		
	D1501	MTZJ13C-T2	Z DIODE		
	D1503	MTZJ13C-T2	Z DIODE		
	D1504	MTZJ13C-T2	Z DIODE		
	D1505	MTZJ13C-T2	Z DIODE		
	D1506	MTZJ8.2C-T2	Z DIODE		
	D1507	1SS133-T2	SI DIODE		
	D1508	1SS133-T2	SI DIODE		
	EP501	E409182-001SM	GRAND TERMINAL		
	EP502	QNZ0136-001Z	EARTH PLATE		
	EP511	E409182-001SM	GRAND TERMINAL		
	FL501	QQR0590-001	FILTER		
	FL502	QQR0590-001	FILTER		
	FW501	QUM132-06Z4Z4	PARA RIBON WIRE		
	HS512	E70306-001	HEAT SINK		
	HS513	E70306-001	HEAT SINK		
	HS514	E70306-001	HEAT SINK		
	HS515	E70306-001	HEAT SINK		
	HS520	E70306-001	HEAT SINK		
	HS521	E70306-001	HEAT SINK		
	HS526	E70306-001	HEAT SINK		
	IC501	M61501FP	IC		
	IC503	BA15218F-XE	IC		
	IC511	NJM2246M-X	IC		
	IC512	NJM2246M-X	IC		
	IC513	NJM2246M-X	IC		
	IC514	NJM2293M-W	IC		
	IC515	NJM2279M-W	IC		
	IC516	NJM2267M-W	IC		
	J 501	QNZ0502-001	RGB CONNECTOR	DVD	
	J 502	QNZ0502-001	RGB CONNECTOR	STB	
	J 503	QNN0163-001	PIN JACK		
	J 504	QNN0060-001	PIN JACK	SUBWOOFER OUT	
	J1501	QNZ0502-001	RGB CONNECTOR	VCR	
	J1502	QNZ0502-001	RGB CONNECTOR	TV	
	K 501	NRSA63J-0R0X	MG RESISTOR		
	K 502	NRSA63J-0R0X	MG RESISTOR		
	O 501	2SC3576-JVC-T	TRANSISTOR		
	O 502	2SC3576-JVC-T	TRANSISTOR		
	O 503	2SC3576-JVC-T	TRANSISTOR		
	Q 505	2SC3576-JVC-T	TRANSISTOR		
	O 506	2SC3576-JVC-T	TRANSISTOR		
	Q 507	2SC3576-JVC-T	TRANSISTOR		
	O 508	2SC3576-JVC-T	TRANSISTOR		
	O 509	DTA114YKA-X	TRANSISTOR		
△	Q 510	KTA1271/OY/-T	TRANSISTOR		
△	O 511	KTC3203/OY/-T	TRANSISTOR		
△	O 512	KTA1046/Y/	TRANSISTOR		
△	O 513	2SD2395/EF/	TRANSISTOR		
△	O 514	2SD2395/EF/	TRANSISTOR		
△	O 515	2SD2395/EF/	TRANSISTOR		
	O 516	DTA114YKA-X	TRANSISTOR		
	O 517	DTC114EKA-X	TRANSISTOR		
△	O 518	KTC3203/OY/-T	TRANSISTOR		
	O 519	DTC114EKA-X	TRANSISTOR		
△	O 520	2SD2395/EF/	TRANSISTOR		
△	O 521	2SD2395/EF/	TRANSISTOR		
	O 522	DTA114EKA-X	D TRANSISTOR		
	O 523	DTC114EKA-X	TRANSISTOR		
	O 524	DTA114EKA-X	D TRANSISTOR		

△	Item	Parts number	Parts name	Remarks	Area
	O 525	DTA114EKA-X	D TRANSISTOR		
△	O 526	2SD2395/EF/	TRANSISTOR		
	O1501	DTC114TKA-X	TRANSISTOR		
	O1502	DTC114TKA-X	TRANSISTOR		
	Q1503	DTC114TKA-X	TRANSISTOR		
	O1504	KTA1267/YG/-T	TRANSISTOR		
	O1505	KTA1267/YG/-T	TRANSISTOR		
	O1506	KTA1267/YG/-T	TRANSISTOR		
	O1514	DTC114EKA-X	TRANSISTOR		
	Q1515	DTC114EKA-X	TRANSISTOR		
	O1520	DTC114EKA-X	TRANSISTOR		
	O1521	DTC114TKA-X	TRANSISTOR		
	O1522	DTC114TKA-X	TRANSISTOR		
	O1523	2SC3576-JVC-T	TRANSISTOR		
	O1524	2SC3576-JVC-T	TRANSISTOR		
	O1525	2SC3576-JVC-T	TRANSISTOR		
	O1526	2SC3576-JVC-T	TRANSISTOR		
	O1527	KTA1267/YG/-T	TRANSISTOR		
	O1528	KTA1267/YG/-T	TRANSISTOR		
	O1531	DTA114YKA-X	TRANSISTOR		
	O1532	DTA114YKA-X	TRANSISTOR		
	R 501	NRSA63J-471X	MG RESISTOR		
	R 502	NRSA63J-471X	MG RESISTOR		
	R 503	NRSA63J-750X	MG RESISTOR		
	R 504	NRSA63J-331X	MG RESISTOR		
	R 505	NRSA63J-750X	MG RESISTOR		
	R 506	NRSA63J-331X	MG RESISTOR		
	R 507	NRSA63J-750X	MG RESISTOR		
	R 508	NRSA63J-331X	MG RESISTOR		
	R 509	NRSA63J-750X	MG RESISTOR		
	R 510	NRSA63J-750X	MG RESISTOR		
	R 511	NRSA63J-331X	MG RESISTOR		
	R 513	NRSA63J-471X	MG RESISTOR		
	R 514	NRSA63J-471X	MG RESISTOR		
	R 515	NRSA63J-750X	MG RESISTOR		
	R 516	NRSA63J-331X	MG RESISTOR		
	R 517	NRSA63J-750X	MG RESISTOR		
	R 518	NRSA63J-331X	MG RESISTOR		
	R 519	NRSA63J-750X	MG RESISTOR		
	R 520	NRSA63J-331X	MG RESISTOR		
	R 521	NRSA63J-750X	MG RESISTOR		
	R 522	NRSA63J-750X	MG RESISTOR		
	R 523	NRSA63J-331X	MG RESISTOR		
	R 525	NRSA63J-471X	MG RESISTOR		
	R 526	NRSA63J-471X	MG RESISTOR		
	R 527	NRSA63J-471X	MG RESISTOR		
	R 528	NRSA63J-471X	MG RESISTOR		
	R 529	NRSA63J-102X	MG RESISTOR		
	R 530	NRSA63J-102X	MG RESISTOR		
	R 531	NRSA63J-103X	MG RESISTOR		
	R 532	NRSA63J-103X	MG RESISTOR		
	R 533	NRSA63J-472X	MG RESISTOR		
	R 534	NRSA63J-472X	MG RESISTOR		
	R 535	NRSA63J-103X	MG RESISTOR		
	R 536	NRSA63J-103X	MG RESISTOR		
	R 537	NRSA63J-103X	MG RESISTOR		
	R 538	NRSA63J-103X	MG RESISTOR		
△	R 541	QRJ146J-2R2X	UNF C RESISTOR	2.2 5% 1/4W	
△	R 542	QRJ146J-2R2X	UNF C RESISTOR	2.2 5% 1/4W	
	R 545	NRSA63J-104X	MG RESISTOR		
	R 546	NRSA63J-104X	MG RESISTOR		
	R 547	NRSA63J-102X	MG RESISTOR		
	R 548	NRSA63J-102X	MG RESISTOR		

■ Electrical parts list (Audio signal input board)

Block No. 03

△	Item	Parts number	Parts name	Remarks	Area
	R 549	NRSA63J-103X	MG RESISTOR		
	R 550	NRSA63J-103X	MG RESISTOR		
	R 552	NRSA63J-104X	MG RESISTOR		
	R 554	NRSA63J-273X	MG RESISTOR		
	R 556	NRSA63J-102X	MG RESISTOR		
	R 557	NRSA63J-104X	MG RESISTOR		
	R 558	NRSA63J-104X	MG RESISTOR		
	R 559	NRSA63J-102X	MG RESISTOR		
	R 561	NRSA63J-103X	MG RESISTOR		
	R 569	NRSA63J-104X	MG RESISTOR		
	R 570	NRSA63J-104X	MG RESISTOR		
	R 571	NRSA63J-102X	MG RESISTOR		
	R 572	NRSA63J-102X	MG RESISTOR		
	R 573	NRSA63J-103X	MG RESISTOR		
	R 574	NRSA63J-103X	MG RESISTOR		
	R 575	NRSA63J-472X	MG RESISTOR		
	R 576	NRSA63J-472X	MG RESISTOR		
△	R 577	QRJ146J-220X	UNF C RESISTOR	22 5% 1/4W	
	R 578	NRSA63J-102X	MG RESISTOR		
△	R 579	QRZ9005-680X	F RESISTOR	68 1/0W	
△	R 580	QRZ9005-680X	F RESISTOR	68 1/0W	
△	R 581	QRZ9005-100X	F RESISTOR	10 1/0W	
△	R 582	QRJ146J-222X	UNF C RESISTOR	2.2K 5% 1/4W	
△	R 583	QRZ9005-100X	F RESISTOR	10 1/0W	
△	R 584	QRJ146J-222X	UNF C RESISTOR	2.2K 5% 1/4W	
△	R 585	QRZ9005-100X	F RESISTOR	10 1/0W	
△	R 586	QRJ146J-182X	UNF C RESISTOR	1.8K 5% 1/4W	
△	R 588	QRJ146J-182X	UNF C RESISTOR	1.8K 5% 1/4W	
△	R 589	QRZ9005-120X	F RESISTOR	12 1/0W	
△	R 590	QRJ146J-682X	UNF C RESISTOR	6.8K 5% 1/4W	
△	R 591	QRZ9006-4R7X	F RESISTOR	4.7 1/0W	
△	R 592	QRZ9006-4R7X	F RESISTOR	4.7 1/0W	
△	R 593	QRJ146J-272X	UNF C RESISTOR	2.7K 5% 1/4W	
△	R 594	QRZ9006-5R6X	F RESISTOR	5.6 1/0W	
△	R 595	QRZ9005-100X	F RESISTOR	10 1/0W	
△	R 596	QRJ146J-102X	UNF C RESISTOR	1.0K 5% 1/4W	
△	R 597	QRZ9006-4R7X	F RESISTOR	4.7 1/0W	
△	R 598	QRJ146J-182X	UNF C RESISTOR	1.8K 5% 1/4W	
△	R 599	QRZ9006-4R7X	F RESISTOR	4.7 1/0W	
△	R 602	QRK126J-120X	UNF C RESISTOR	12 5% 1/2W	
△	R 603	QRK126J-3R9X	C RESISTOR	3.9 5% 1/2W	
	R1501	NRSA63J-101X	MG RESISTOR		
	R1502	NRSA63J-101X	MG RESISTOR		
	R1503	NRSA63J-471X	MG RESISTOR		
	R1504	NRSA63J-471X	MG RESISTOR		
	R1505	NRSA63J-750X	MG RESISTOR		
	R1506	NRSA63J-331X	MG RESISTOR		
	R1507	NRSA63J-473X	MG RESISTOR		
	R1508	NRSA63J-750X	MG RESISTOR		
	R1509	NRSA63J-750X	MG RESISTOR		
	R1510	NRSA63J-331X	MG RESISTOR		
	R1511	NRSA63J-101X	MG RESISTOR		
	R1512	NRSA63J-101X	MG RESISTOR		
	R1513	NRSA63J-471X	MG RESISTOR		
	R1514	NRSA63J-471X	MG RESISTOR		
	R1515	NRSA63J-750X	MG RESISTOR		
	R1516	NRSA63J-473X	MG RESISTOR		
	R1517	NRSA63J-750X	MG RESISTOR		
	R1518	NRSA63J-473X	MG RESISTOR		
	R1519	NRSA63J-750X	MG RESISTOR		
	R1520	NRSA63J-473X	MG RESISTOR		
	R1521	NRSA63J-750X	MG RESISTOR		
	R1522	NRSA63J-750X	MG RESISTOR		

△	Item	Parts number	Parts name	Remarks	Area
	R1523	NRSA63J-331X	MG RESISTOR		
	R1524	NRSA63J-750X	MG RESISTOR		
	R1525	NRSA63J-473X	MG RESISTOR		
	R1529	NRSA63J-391X	MG RESISTOR		
	R1530	NRSA63J-391X	MG RESISTOR		
	R1531	NRSA63J-391X	MG RESISTOR		
	R1547	NRSA63J-102X	MG RESISTOR		
	R1548	NRSA63J-102X	MG RESISTOR		
	R1549	NRSA63J-104X	MG RESISTOR		
△	R1556	QRJ146J-2R2X	UNF C RESISTOR	2.2 5% 1/4W	
	R1558	NRSA63J-105X	MG RESISTOR		
	R1560	NRSA63J-750X	MG RESISTOR		
	R1561	NRSA63J-751X	MG RESISTOR		
	R1562	NRSA63J-751X	MG RESISTOR		
	R1563	NRSA63J-103X	MG RESISTOR		
	R1564	NRSA63J-103X	MG RESISTOR		
	R1565	NRSA63J-751X	MG RESISTOR		
	R1566	NRSA63J-751X	MG RESISTOR		
	R1567	NRSA63J-103X	MG RESISTOR		
	R1568	NRSA63J-103X	MG RESISTOR		
	R1569	NRSA63J-331X	MG RESISTOR		
	R1570	NRSA63J-750X	MG RESISTOR		
	R1571	NRSA63J-331X	MG RESISTOR		
	R1572	NRSA63J-750X	MG RESISTOR		
	R1573	NRSA63J-511X	MG RESISTOR		
	R1574	NRSA63J-511X	MG RESISTOR		
△	R1575	QRZ9005-101X	F RESISTOR	100 1/0W	
	R1576	NRSA63J-221X	MG RESISTOR		
	R1577	NRSA63J-221X	MG RESISTOR		
	R1578	NRSA63J-221X	MG RESISTOR		
	R1579	NRSA63J-103X	MG RESISTOR		
	R1601	NRSA63J-104X	MG RESISTOR		
	R1602	NRSA63J-104X	MG RESISTOR		
	R1603	NRSA63J-104X	MG RESISTOR		
	R1604	NRSA63J-104X	MG RESISTOR		
	R1605	NRSA63J-301X	MG RESISTOR		
	R1606	NRSA63J-301X	MG RESISTOR		
	R1611	NRSA63J-104X	MG RESISTOR		
	R1612	NRSA63J-104X	MG RESISTOR		
	R1613	NRSA63J-104X	MG RESISTOR		
	R1614	NRSA63J-104X	MG RESISTOR		
	R1615	NRSA63J-104X	MG RESISTOR		
	R1616	NRSA63J-104X	MG RESISTOR		
	R1617	NRSA63J-104X	MG RESISTOR		
	R1618	NRSA63J-104X	MG RESISTOR		
	R1619	NRSA63J-104X	MG RESISTOR		
	R1620	NRSA63J-104X	MG RESISTOR		
	R1621	NRSA63J-102X	MG RESISTOR		
	R1623	QRE141J-820Y	C RESISTOR	82 5% 1/4W	
	R1624	QRE141J-820Y	C RESISTOR	82 5% 1/4W	
△	R1625	QRJ146J-2R2X	UNF C RESISTOR	2.2 5% 1/4W	
△	R1626	QRJ146J-2R2X	UNF C RESISTOR	2.2 5% 1/4W	
	R1631	NQR0269-004X	FERRITE BEADS		
	R1632	NQR0269-004X	FERRITE BEADS		
	R1633	NQR0269-004X	FERRITE BEADS		
	R1634	NQR0269-004X	FERRITE BEADS		

■ Electrical parts list (DSP board)

Block No. 04

▲	Item	Parts number	Parts name	Remarks	Area
	C 601	NCB31HK-221X	C CAPACITOR		
	C 602	NCB31HK-221X	C CAPACITOR		
	C 603	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 604	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 605	NCF31CZ-104X	C CAPACITOR		
	C 606	NCF31CZ-104X	C CAPACITOR		
	C 607	QETN1CM-107Z	E CAPACITOR	100MF 20% 16V	
	C 608	NCF31CZ-104X	C CAPACITOR		
	C 609	NCF31CZ-104X	C CAPACITOR		
	C 610	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 611	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 612	NCB31CK-103X	C CAPACITOR		
	C 621	QETN1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C 622	NCS31HJ-101X	C CAPACITOR		
	C 624	NCF31CZ-104X	C CAPACITOR		
	C 626	NCB31CK-104X	C CAPACITOR		
	C 628	NCB31CK-103X	C CAPACITOR		
	C 631	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 632	NCB31CK-103X	C CAPACITOR		
	C 633	NCF31CZ-104X	C CAPACITOR		
	C 634	NCF31CZ-104X	C CAPACITOR		
	C 635	NCF31CZ-104X	C CAPACITOR		
	C 636	NCB31CK-473X	C CAPACITOR		
	C 638	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 639	NCB31CK-103X	C CAPACITOR		
	C 641	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 642	NCB31CK-103X	C CAPACITOR		
	C 643	NCB31AK-474X	C CAPACITOR		
	C 644	NCB31CK-103X	C CAPACITOR		
	C 645	NCS31HJ-101X	C CAPACITOR		
	C 646	NCB31CK-103X	C CAPACITOR		
	C 647	NCS31HJ-220X	C CAPACITOR		
	C 648	NCS31HJ-180X	C CAPACITOR		
	C 649	NCS31HJ-121X	C CAPACITOR		
	C 653	NCB31CK-104X	C CAPACITOR		
	C 654	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 661	NCB31CK-103X	C CAPACITOR		
	C 671	NCB31CK-103X	C CAPACITOR		
	C 672	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 673	NCB31CK-103X	C CAPACITOR		
	C 677	NCS31HJ-101X	C CAPACITOR		
	C 679	NCS31HJ-101X	C CAPACITOR		
	C 681	NCB31CK-103X	C CAPACITOR		
	C 682	NCB31CK-103X	C CAPACITOR		
	C 683	NCB31CK-103X	C CAPACITOR		
	C 684	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 685	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C 686	QETN1CM-476Z	E CAPACITOR	47MF 20% 16V	
	C 687	NCB31CK-103X	C CAPACITOR		
	C 688	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 689	NCB31CK-103X	C CAPACITOR		
	C 690	QETN0JM-107Z	E CAPACITOR	100MF 20% 6.3V	
	C 693	NCB31CK-103X	C CAPACITOR		
	C 694	NCB31CK-104X	C CAPACITOR		
	CN681	QGB2510K1-20	B TO B CONNE		
	C2500	QETN1CM-226Z	E CAPACITOR	22MF 20% 16V	
	C2503	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C2504	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C2507	NCS31HJ-330X	C CAPACITOR		
	C2508	NCS31HJ-330X	C CAPACITOR		
	C2512	NCF31CZ-104X	C CAPACITOR		
	C2513	NCB31HK-122X	C CAPACITOR		
	C2514	NCB31HK-122X	C CAPACITOR		

▲	Item	Parts number	Parts name	Remarks	Area
	C2515	NCS31HJ-121X	C CAPACITOR		
	C2516	NCS31HJ-121X	C CAPACITOR		
	C2517	NCS31HJ-391X	C CAPACITOR		
	C2518	NCS31HJ-391X	C CAPACITOR		
	C2525	NCB31HK-102X	C CAPACITOR		
	C2526	NCB31HK-102X	C CAPACITOR		
	C2527	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C2528	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C2531	NCS31HJ-560X	C CAPACITOR		
	C2532	NCS31HJ-560X	C CAPACITOR		
	C2533	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C2534	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C2539	NCF31CZ-104X	C CAPACITOR		
	C2540	NCF31CZ-104X	C CAPACITOR		
	C2551	NCS31HJ-560X	C CAPACITOR		
	C2552	NCS31HJ-560X	C CAPACITOR		
	C2555	NCF31CZ-104X	C CAPACITOR		
	C2556	NCF31CZ-104X	C CAPACITOR		
	C2561	QETN1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C2562	QETN1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C2563	NCS31HJ-220X	C CAPACITOR		
	C2564	NCS31HJ-220X	C CAPACITOR		
	C2569	NCF31CZ-104X	C CAPACITOR		
	C2570	NCF31CZ-104X	C CAPACITOR		
	C2575	NCB31HK-102X	C CAPACITOR		
	C2576	NCB31HK-102X	C CAPACITOR		
	C2577	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C2578	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C2581	QETN1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C2582	QETN1CM-106Z	E CAPACITOR	10MF 20% 16V	
	C2583	NCS31HJ-220X	C CAPACITOR		
	C2584	NCS31HJ-560X	C CAPACITOR		
	C2585	NCF31CZ-104X	C CAPACITOR		
	C2586	NCF31CZ-104X	C CAPACITOR		
	C2587	NCS31HJ-560X	C CAPACITOR		
	C2588	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	C2589	NCF31CZ-104X	C CAPACITOR		
	C2590	NCF31CZ-104X	C CAPACITOR		
	C2592	NCB31HK-223X	C CAPACITOR		
	C2594	NCF31CZ-104X	C CAPACITOR		
	C2595	NCB31HK-102X	C CAPACITOR		
	C2597	QETN1HM-106Z	E CAPACITOR	10MF 20% 50V	
	C2598	QETN1HM-475Z	E CAPACITOR	4.7MF 20% 50V	
	D 607	1SS355-X	DIODE		
	D 608	1SS355-X	DIODE		
	IC601	AK4527BVQ	IC		
	IC609	BA15218F-XE	IC		
	IC610	BA15218F-XE	IC		
	IC611	BU4066BCF-X	IC		
	IC621	TC7SU04FU-X	IC		
	IC622	TC7SU04FU-X	IC		
	IC631	TC9446F-014	IC		
	IC641	W24L010AJ-12-X	IC		
	IC650	BA15218F-XE	IC		
	IC651	BA15218F-XE	IC		
	IC652	IMX9-W	TRANSISTOR		
	IC661	BA15218F-XE	IC		
	IC662	IMX9-W	TRANSISTOR		
	IC671	UPD784215AGC103	IC		
	IC672	TC7SET32FU-X	IC		
	IC681	PQ3DZ53-X	IC		
	IC682	IMX9-W	TRANSISTOR		
	IC683	RN5RZ33BA-X	IC		

■ Electrical parts list (DSP board)

Block No. 04

△	Item	Parts number	Parts name	Remarks	Area
	IC690	BA15218F-XE	IC		
	IC691	BA15218F-XE	IC		
	J 601	QNN0347-001	PIN JACK		
	K 601	NQR0269-004X	FERRITE BEADS		
	K 603	NQR0269-004X	FERRITE BEADS		
	K 681	NQR0319-001X	F BEADS		
	K 682	NQR0319-001X	F BEADS		
	K 687	NQR0319-001X	F BEADS		
	K 688	NQR0319-001X	F BEADS		
	LC631	NQR0321-001X	EMI FILTER		
	O 601	DTC114YE-X	TRANSISTOR		
	O 607	DTA144EKA-X	TRANSISTOR		
	O 670	DTC114YE-X	TRANSISTOR		
	O 671	2SD2114K/VW/-X	CHIP TRANSISTOR		
	O 672	DTC114YE-X	TRANSISTOR		
	O 673	DTA144EKA-X	TRANSISTOR		
	O2501	DTA144EKA-X	TRANSISTOR		
	R 600	NRSA63J-0R0X	MG RESISTOR		
	R 601	NRSA63J-473X	MG RESISTOR		
	R 602	NRSA63J-473X	MG RESISTOR		
	R 603	NRSA63J-473X	MG RESISTOR		
	R 606	NRSA63J-221X	MG RESISTOR		
	R 607	NRSA63J-221X	MG RESISTOR		
	R 608	NRSA63J-221X	MG RESISTOR		
	R 609	NRSA63J-221X	MG RESISTOR		
	R 611	NRSA63J-221X	MG RESISTOR		
	R 612	NRSA63J-221X	MG RESISTOR		
	R 613	NRSA63J-822X	MG RESISTOR		
	R 615	NRSA63J-432X	MG RESISTOR		
	R 617	NRSA63J-103X	MG RESISTOR		
	R 618	NRSA63J-103X	MG RESISTOR		
	R 621	NRSA63J-221X	MG RESISTOR		
	R 622	NRSA63J-750X	MG RESISTOR		
	R 623	NRSA63J-101X	MG RESISTOR		
	R 627	NRSA63J-472X	MG RESISTOR		
	R 628	NRSA63J-183X	MG RESISTOR		
	R 632	NRSA63J-0R0X	MG RESISTOR		
	R 633	NRSA63J-221X	MG RESISTOR		
	R 639	NRSA63J-472X	MG RESISTOR		
	R 640	NRSA63J-0R0X	MG RESISTOR		
	R 641	NRSA63J-102X	MG RESISTOR		
	R 642	NRSA63J-103X	MG RESISTOR		
	R 643	NRSA63J-101X	MG RESISTOR		
	R 644	NRSA63J-563X	MG RESISTOR		
	R 645	NRSA63J-102X	MG RESISTOR		
	R 646	NRSA63J-103X	MG RESISTOR		
	R 647	NRSA63J-225X	MG RESISTOR		
	R 648	NRSA63J-472X	MG RESISTOR		
	R 657	NRSA63J-103X	MG RESISTOR		
	R 661	NRSA63J-221X	MG RESISTOR		
	R 662	NRSA63J-221X	MG RESISTOR		
	R 663	NRSA63J-221X	MG RESISTOR		
	R 664	NRSA63J-221X	MG RESISTOR		
	R 669	NRSA63J-103X	MG RESISTOR		
	R 670	NRSA63J-103X	MG RESISTOR		
	R 671	NRSA63J-103X	MG RESISTOR		
	R 672	NRSA63J-105X	MG RESISTOR		
	R 673	NRSA63J-432X	MG RESISTOR		
	R 674	NRSA63J-432X	MG RESISTOR		
	R 675	NRSA63J-432X	MG RESISTOR		
	R 676	NRSA63J-432X	MG RESISTOR		
	R 677	NRSA63J-822X	MG RESISTOR		
	R 678	NRSA63J-822X	MG RESISTOR		

△	Item	Parts number	Parts name	Remarks	Area
	R 679	NRSA63J-822X	MG RESISTOR		
	R 680	NRSA63J-822X	MG RESISTOR		
	R 681	NRSA63J-103X	MG RESISTOR		
	R 682	NRSA63J-103X	MG RESISTOR		
	R 683	NRSA63J-0R0X	MG RESISTOR		
	R 684	NRSA63J-0R0X	MG RESISTOR		
	R 685	NRSA63J-103X	MG RESISTOR		
	R 686	NRSA63J-151X	MG RESISTOR		
	R 688	NRSA63J-0R0X	MG RESISTOR		
	R 691	NRSA63J-221X	MG RESISTOR		
	R 692	NRSA63J-221X	MG RESISTOR		
	R 693	NRSA63J-221X	MG RESISTOR		
	R 694	NRSA63J-221X	MG RESISTOR		
	R 695	NRSA63J-221X	MG RESISTOR		
	R 696	NRSA63J-221X	MG RESISTOR		
	R2500	NRSA63J-102X	MG RESISTOR		
	R2501	NRSA63J-104X	MG RESISTOR		
	R2502	NRSA63J-104X	MG RESISTOR		
	R2507	NRSA63J-223X	MG RESISTOR		
	R2508	NRSA63J-223X	MG RESISTOR		
	R2509	NRSA63J-223X	MG RESISTOR		
	R2510	NRSA63J-223X	MG RESISTOR		
	R2511	NRSA63J-912X	MG RESISTOR		
	R2512	NRSA63J-912X	MG RESISTOR		
	R2513	NRSA63J-103X	MG RESISTOR		
	R2514	NRSA63J-103X	MG RESISTOR		
	R2515	NRSA63J-103X	MG RESISTOR		
	R2516	NRSA63J-103X	MG RESISTOR		
	R2517	NRSA63J-103X	MG RESISTOR		
	R2518	NRSA63J-103X	MG RESISTOR		
	R2519	NRSA63J-331X	MG RESISTOR		
	R2520	NRSA63J-331X	MG RESISTOR		
	R2521	NRSA63J-331X	MG RESISTOR		
	R2522	NRSA63J-331X	MG RESISTOR		
	R2525	NRSA63J-471X	MG RESISTOR		
	R2526	NRSA63J-471X	MG RESISTOR		
	R2527	NRSA63J-104X	MG RESISTOR		
	R2528	NRSA63J-104X	MG RESISTOR		
	R2529	NRSA63J-103X	MG RESISTOR		
	R2530	NRSA63J-103X	MG RESISTOR		
	R2531	NRSA63J-912X	MG RESISTOR		
	R2532	NRSA63J-912X	MG RESISTOR		
	R2533	NRSA63J-103X	MG RESISTOR		
	R2534	NRSA63J-103X	MG RESISTOR		
	R2535	NRSA63J-103X	MG RESISTOR		
	R2536	NRSA63J-103X	MG RESISTOR		
	R2537	NRSA63J-104X	MG RESISTOR		
	R2538	NRSA63J-104X	MG RESISTOR		
	R2550	NRSA63J-272X	MG RESISTOR		
	R2551	NRSA63J-103X	MG RESISTOR		
	R2552	NRSA63J-103X	MG RESISTOR		
	R2553	NRSA63J-153X	MG RESISTOR		
	R2554	NRSA63J-153X	MG RESISTOR		
	R2555	NRSA63J-752X	MG RESISTOR		
	R2556	NRSA63J-752X	MG RESISTOR		
	R2557	NRSA63J-103X	MG RESISTOR		
	R2558	NRSA63J-223X	MG RESISTOR		
	R2560	NRSA63J-105X	MG RESISTOR		
	R2561	NRSA63J-104X	MG RESISTOR		
	R2562	NRSA63J-104X	MG RESISTOR		
	R2563	NRSA63J-103X	MG RESISTOR		
	R2564	NRSA63J-103X	MG RESISTOR		
	R2565	NRSA63J-302X	MG RESISTOR		

■ Electrical parts list (DSP board) Block No. 04

△	Item	Parts number	Parts name	Remarks	Area
	R2566	NRSA63J-302X	MG RESISTOR		
	R2567	NRSA63J-103X	MG RESISTOR		
	R2568	NRSA63J-103X	MG RESISTOR		
	R2575	NRSA63J-102X	MG RESISTOR		
	R2576	NRSA63J-102X	MG RESISTOR		
	R2577	NRSA63J-104X	MG RESISTOR		
	R2578	NRSA63J-104X	MG RESISTOR		
	R2581	NRSA63J-104X	MG RESISTOR		
	R2582	NRSA63J-104X	MG RESISTOR		
	R2583	NRSA63J-103X	MG RESISTOR		
	R2584	NRSA63J-223X	MG RESISTOR		
	R2585	NRSA63J-272X	MG RESISTOR		
	R2586	NRSA63J-332X	MG RESISTOR		
	R2587	NRSA63J-103X	MG RESISTOR		
	R2588	NRSA63J-103X	MG RESISTOR		
	R2589	NRSA63J-104X	MG RESISTOR		
	R2590	NRSA63J-333X	MG RESISTOR		
	R2592	NRSA63J-333X	MG RESISTOR		
	R2594	NRSA63J-333X	MG RESISTOR		
	R2595	NRSA63J-102X	MG RESISTOR		
	R2596	NRSA63J-102X	MG RESISTOR		
	R2597	NRSA63J-104X	MG RESISTOR		
	R2598	NRSA63J-104X	MG RESISTOR		
	UN661	GP1FA550RZ	OPT RECEIVER		
	X 631	NAX0385-001X	CRYSTAL		
	X 671	NAX0275-001X	1COSCIALLATOR		

■ Electrical parts list (Tuner board)

Block No. 05

△	Item	Parts number	Parts name	Remarks	Area
	AT101	QNB0014-001	ANT TERMINAL		
	BK 1	LV31618-001A	SHIELD BKT		
	C 101	NCB21HK-103X	C CAPACITOR		
	C 103	NCB21HK-223X	C CAPACITOR		
	C 105	NCB21HK-223X	C CAPACITOR		
	C 107	QEK1CM-226Z	E CAPACITOR	22MF 20% 16V	
	C 111	NCB21HK-473X	C CAPACITOR		
	C 112	NDC21HJ-120X	C CAPACITOR		
	C 113	QCSB1HJ-120Y	C CAPACITOR	12PF 5% 50V	
	C 121	NDC21HJ-120X	C CAPACITOR		
	C 122	NDC21HJ-120X	C CAPACITOR		
	C 123	NCB21HK-473X	C CAPACITOR		
	C 126	NCS21HJ-101X	C CAPACITOR		
	C 128	QENC1HM-474Z	NP E CAPACITOR	.47MF 20% 50V	
	C 129	NCB21HK-102X	C CAPACITOR		
	C 130	QEK1AM-107Z	E CAPACITOR	100MF 20% 10V	
	C 133	QEK1CM-226Z	E CAPACITOR	22MF 20% 16V	
	C 134	NCB21HK-222X	C CAPACITOR		
	C 135	NCB21HK-223X	C CAPACITOR		
	C 136	QEK1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C 137	NCS21HJ-680X	C CAPACITOR		
	C 139	NCB21HK-393X	C CAPACITOR		
	C 140	NCB21HK-393X	C CAPACITOR		
	C 141	NCB21HK-473X	C CAPACITOR		
	C 143	NCB21HK-223X	C CAPACITOR		
	C 144	NCB21HK-473X	C CAPACITOR		
	C 146	QEK1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C 147	QEK1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C 148	QEK1HM-224Z	E CAPACITOR	.22MF 20% 50V	
	C 149	QEK1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C 150	QEK1CM-226Z	E CAPACITOR	22MF 20% 16V	
	C 156	QDGB1HK-102Y	C CAPACITOR		
	C 157	NCB21HK-473X	C CAPACITOR		
	C 158	QEK1CM-226Z	E CAPACITOR	22MF 20% 16V	
	C 161	QEK1CM-106Z	E CAPACITOR	10MF 20% 16V	
	C 162	QEK1CM-106Z	E CAPACITOR	10MF 20% 16V	
	C 163	NCB21HK-223X	C CAPACITOR		
	C 164	NCB21HK-473X	C CAPACITOR		
	C 168	QEK1HM-105Z	E CAPACITOR	1.0MF 20% 50V	
	C 184	QEK1CM-107Z	E CAPACITOR	100MF 20% 16V	
	C 185	QEK1CM-106Z	E CAPACITOR	10MF 20% 16V	
	C 186	QEK1CM-106Z	E CAPACITOR	10MF 20% 16V	
	C 191	NCS21HJ-820X	C CAPACITOR		
	C 192	NCS21HJ-470X	C CAPACITOR		
	C 193	NCB21HK-561X	C CAPACITOR		
	C 194	NCB21HK-104X	C CAPACITOR		
	C 195	NCB21HK-331X	C CAPACITOR		
	C 196	QEK1HM-225Z	E CAPACITOR	2.2MF 20% 50V	
	C 197	NCB21HK-473X	C CAPACITOR		
	C 199	QEK1CM-106Z	E CAPACITOR	10MF 20% 16V	
	CF101	QAX0285-001Z	C FILTER		
	CF102	QAX0285-001Z	C FILTER		
	CF103	QAX0519-001Z	C FILTER		
	CN111	QGB2501K2-12	CONECTOR		
	CN112	QGB2501K1-04	CONNECTOR		
	D 121	1SS133-T2	SI DIODE		
	D 123	1SS133-T2	SI DIODE		
	D 129	1SS133-T2	SI DIODE		
	D 131	1SS133-T2	SI DIODE		
	IC102	LA1838	IC		
	IC121	LC72136N	IC		
	IC191	SAA6588	IC(RDS)		
	L 112	QQL231K-2R7Y	INDUCTOR		

△	Item	Parts number	Parts name	Remarks	Area
	O 102	2SC535/BC/-T	TRANSISTOR		
	O 103	2SC461/BC/-T	TRANSISTOR		
	O 111	KTC3199/GL/-T	TRANSISTOR		
	O 112	KTC3199/GL/-T	TRANSISTOR		
	O 113	DTA114YKA-X	TRANSISTOR		
	O 121	KRA103M-T	TRANSISTOR		
	R 103	NRSA02J-221X	MG RESISTOR		
	R 104	NRSA02J-272X	MG RESISTOR		
	R 105	NRSA02J-391X	MG RESISTOR		
	R 106	NRSA02J-102X	MG RESISTOR		
	R 107	NRSA02J-561X	MG RESISTOR		
	R 108	NRSA02J-332X	MG RESISTOR		
	R 109	NRSA02J-221X	MG RESISTOR		
	R 111	NRSA02J-182X	MG RESISTOR		
	R 112	QRE141J-182Y	C RESISTOR	1.8K 5% 1/4W	
	R 114	NRSA02J-272X	MG RESISTOR		
	R 115	NRSA02J-104X	MG RESISTOR		
	R 119	NRSA02J-103X	MG RESISTOR		
	R 122	NRSA02J-472X	MG RESISTOR		
	R 124	NRSA02J-222X	MG RESISTOR		
	R 126	NRSA02J-562X	MG RESISTOR		
	R 127	NRSA02J-822X	MG RESISTOR		
	R 128	NRSA02J-472X	MG RESISTOR		
	R 129	NRSA02J-222X	MG RESISTOR		
	R 130	QRZ9005-680X	F RESISTOR	68 1/0W	
	R 132	NRSA02J-393X	MG RESISTOR		
	R 133	NRSA02J-392X	MG RESISTOR		
	R 134	NRSA02J-102X	MG RESISTOR		
	R 140	NRSA02J-473X	MG RESISTOR		
	R 141	NRSA02J-102X	MG RESISTOR		
	R 142	NRSA02J-470X	MG RESISTOR		
	R 143	NRSA02J-562X	MG RESISTOR		
	R 144	NRSA02J-332X	MG RESISTOR		
	R 145	NRSA02J-103X	MG RESISTOR		
	R 146	NRSA02J-472X	MG RESISTOR		
	R 147	NRSA02J-332X	MG RESISTOR		
	R 150	NRSA02J-331X	MG RESISTOR		
	R 157	NRSA02J-332X	MG RESISTOR		
	R 158	NRSA02J-332X	MG RESISTOR		
	R 161	NRSA02J-102X	MG RESISTOR		
	R 162	NRSA02J-102X	MG RESISTOR		
	R 182	NRSA02J-103X	MG RESISTOR		
	R 183	NRSA02J-103X	MG RESISTOR		
	R 184	NRSA02J-103X	MG RESISTOR		
	R 191	NRSA02J-102X	MG RESISTOR		
	R 192	NRSA02J-474X	MG RESISTOR		
	R 193	NRSA02J-103X	MG RESISTOR		
	R 194	NRSA02J-103X	MG RESISTOR		
	RF101	QAU0119-001	FRONT END	FOR FTZ	
	T 111	QQR0871-001	COIL BLOCK		
	T 142	QQR0973-001	IFT		
	X 121	QAX0402-001	CRYSTAL		
	X 191	QAX0263-001Z	CRYSTAL		

Packing materials and accessories parts list


Block No.

M	2	M	M
---	---	---	---


Block No.

M	3	M	M
---	---	---	---

Ver.E/EN



Ver.B



■ Parts list (Packing)

Block No. M2MM


⚠	Item	Parts number	Parts name	Q'ty	Description	Area
	P 1	LV20978-006A	CARTON BOX	1	RX-E100RSL	E, EN
		LV20978-007A	CARTON BOX	1	RX-E100RSB	E, EN
		LV20978-001A	CARTON BOX	1	RX-E100RSL	B
	P 2	LV20963-001A	CUSHION(FRONT)	1		
	P 3	LV20964-001A	CUSHION(REAR)	1		
	P 4	LV32804-001A	PACKING SHEET	1		B
	P 5	QPC06507015P	POLY BAG	1	FOR SET	
	P 6	QPA02503505P	POLY BAG	1	FOR INST	
	P 7	LV32034-005A	SHEET	2		E, EN

■ Parts list (Accessories)


Block No. M3MM

⚠	Item	Parts number	Parts name	Q'ty	Description	Area
	A 1	RM-SRXE100R	REMOCON	1		
	A 2	-----	BATTERY	2		
	A 3	LVT0650-003A	INST BOOK	1	ENG	B
		LVT0650-005A	INST BOOK	1	SWE, FIN, DAN, GER	EN
		LVT0650-005A	INST BOOK	1	FRE, SPA, ITA	EN
		LVT0650-004A	INST BOOK	1	GER, FRE, DUT	E
	A 4	EWP503-001C	ANT.WIRE	1		
	A 5	QAL0204-001	AM LOOP ANT	1		
	A 6	E43486-340A	BS=SAFETY INST	1		B
	A 7	VNA3000-204	REGIST.CARD	1		B
	A 8	BT-54013-1	WARRANTY CARD	1		E
		BT-54008-2	WARRANTY CARD	1		B, EN


Block diagram




■ Speaker terminal section




■ Audio amp section



FROM CN715 OF LVA10229-2
(SHEET 2/8)



FROM CN711 OF LVA10229-2
(SHEET 2/8)




FROM CN712 OF LVA10229-
(SHEET 2/8)


*MARK LIST

	B. E. EN	J. C
R303, 304	68k	56k
R307, 308	2k	3, 3k
R315-316	120 UNF (1/4W)	330 UNF (1/4W)
R319-320	470 UNF (1/4W)	330 UNF (1/4W)
R335-338	82	120
R835-838	100	180
R935	100	180
R937	100	180
C317, 318	33/50	2, 2/50

	B, E, EN	J, C
C311, 312	10p	22p
C811, 812	10p	22p
C911	10p	22p
C303, 304	68p	270p
C803, 804	68p	270p
C903	68p	270p
C305, 306	220p	100p
C805, 806	220p	100p
C905	220p	100p



FROM CN713 OF LVA10229-2
(SHEET 2/8)




FROM CN714 OF LVA10229-2
(SHEET 2/8)

 FRONT signal
 CENTER signal
 SURROUND signal

 Parts are safety assurance parts. When replacing those parts make sure to use the specified.

■ Audio signal input terminal section

-  DSP signal
-  TUNER signal
-  TV Audio signal
-  FRONT signal
-  SUB WOOFER signal
-  VCR Audio signal
-  CENTER signal
-  DVD Audio signal
-  SURROUND signal




■ Video & Audio input terminal section

4

3

2

1



 Parts are safety assurance parts. When replacing those parts make sure to use the specified.

➔ TV Audio signal
➔ VCR Audio signal

A	B	C	2-6	D	E	F	G	H
---	---	---	-----	---	---	---	---	---



■ DSP section


5

4

3

2


1



FROM CN601 OF LVA10212-1
(SHEET 4/8)

⇐ DSP signal
⇐ FRONT signal
⇐ CENTER signal
⇐ SURROUND signal

■ Tuner section




▲ Parts are safety assurance parts.
When replacing those parts make
sure to use the specified one.


➡ TUNER signal

Printed circuit boards

■ Main & System control board



■ **Audio signal input board**



■ power amp. board



■ Tuner board

